



The Odr Handbook

Everything your restaurant runs on — the floor, the kitchen, the bill and the QR menu. Written for waiters, cashiers and owners. No jargon.

Point of sale for restaurants that run on rhythm · Made in Mangaluru
Version 1.0 · FY 2026–27

Powered by **zowcode.com** · hello@zowcode.com

SECTION 01

What Odr is

Four screens. One restaurant.

Odr replaces the billing machine, the KOT pad and the printed menu. Everything runs in a normal web browser — on a phone, a tablet, the counter computer or a TV in the kitchen. There is nothing to install.

SCREEN	WHO USES IT	WHAT IT DOES
Captain	Waiters, cashier, owner	Open tables, take orders, fire the kitchen, settle and print the bill.
Kitchen	Cooks	A live list of what to cook. Tap Done when a dish leaves the pass.
QR menu	Diners	Scan the table code, browse the menu, order. No app, no login.
Admin	Odr team only	Sets up your restaurant and your subscription.

No payments inside Odr

Odr never takes money. Diners pay at the counter — cash, UPI, card, however you already do it. Odr records what was ordered and prints the bill.

Words you will see

Order	Everything one table (or one parcel) has asked for.
KOT	Kitchen Order Ticket — the slip that tells the kitchen to start cooking.
Fire	Send the items to the kitchen.
Settle	Close the order and produce the bill.
Void	Cancel an order opened by mistake.
Off-table	Parcel, Zomato, Swiggy — an order with no table.

SECTION 02

Starting your shift

Sign in once. Stay signed in all day.

- 1 Open the Odr address in the browser. Bookmark it, or add it to the home screen so it opens like an app.
- 2 Type your email and password. Tap **Begin shift**.
- 3 If you work at more than one restaurant, pick the one you are in today.
- 4 If your restaurant has more than one outlet and you are an owner or manager, pick the outlet you are in. Odr remembers it on this device.
- 5 You land on the **Tables** screen. You are ready.

More than one outlet

One Odr account can run several outlets of the same brand. Everything that happens on the floor — tables, orders, kitchen tickets, bills and invoice numbers — belongs to one outlet.

Owner, manager	See every outlet. Tap the outlet name in the top bar to switch. The floor, kitchen and sales screens change to that outlet.
Captain, cashier, kitchen	Belong to one outlet, chosen when the owner adds them. They sign straight into it and cannot see the others.
Menu	Outlets usually share the brand menu. Sold out is marked per outlet, so a dish finished at one branch stays on sale at the next. An outlet can instead have its own menu — ask Odr when the outlet is set up.
Sales	Owners and managers get an All outlets switch on the Sales screen with a total per outlet.
Adding an outlet	Done by the Odr team — pricing is per outlet. You then fill in its name, GSTIN, address and invoice prefix under Settings → Outlet.

The bar across the top

- **Outlet name and your email** — check you are in the right place. With several outlets the name is a button: tap it to switch.
- **Connected / Working offline** — tells you whether the internet is reachable.
- **Sun / moon** — switches between light and dark. Dark is easier at night.
- **Icons** — Tables, Kitchen, Settings, Sign out.

If a yellow strip appears

Your subscription is ending within 7 days. Tell the owner to contact Odr. When it runs out the screen locks and no orders can be taken.

Who can do what

Each role is the one below it plus a little more. Nobody is ever blocked from serving a customer — the differences are only about money and settings.

ROLE	ADDS ON TOP OF THE ROW ABOVE
Captain	Open tables, take orders, add items at any time, fire KOTs.
Cashier	... and settle orders, make and print bills.
Manager	... and void orders, edit the menu, change tables and printer settings. Can see the staff list.
Owner	... and add or remove staff. The owner can do everything .
Kitchen	A read-only login for a kitchen screen. Cannot take or change orders.

A one- or two-person restaurant: sign in as the owner

If the same person seats the table, takes the order, cooks or plates, and takes the money, they should use the

owner

login and nothing else. Owner includes every captain, cashier and manager ability, so one person runs the whole floor from one screen. Only create captain or cashier logins once you actually have separate staff and want to limit what they can reach.

There is no "switch role" button, and it would not help: an owner already has every ability a captain or cashier has. Switching down would only take abilities away. If a waiter is busy, the owner just does the task on their own screen.

SECTION 03

The floor

One screen that shows the whole restaurant. It refreshes itself every 5 seconds.

The four numbers at the top

Occupied	Tables with an order running.
Ready to bill	Tables whose food has been fired — likely eating now.
Free	Tables you can seat someone at.
Open value	Money currently sitting on the floor, unbilled.

Reading a table tile

- **FREE** — nobody seated. Tap it to open an order.
- **Open** — order started, nothing ordered yet.
- **Adding** — items on the order, not yet sent to the kitchen.
- **Fired** — the kitchen is cooking.
- A green **QR** badge means the diner ordered from their own phone.
- A number in the corner (46m) is how long the table has been running. Over 30 minutes the tile gets an outline — worth a look.

Filters

All · Occupied · Ready to bill · Free. During a rush, tap *Ready to bill* to see only the tables that may want the cheque.

Off-table strip

Parcels and Zomato/Swiggy orders appear in their own row above the tables, so they never get lost between the tables.

SECTION 04

Taking an order

The screen every waiter lives in. It works with one thumb on a phone.

- 1 Tap a **free table**. The order opens straight away.
- 2 Pick a category (Dosa, Drinks, Snacks) or type in **Search the menu** — search looks at the whole menu, not just the open category.
- 3 Tap  on a dish to add it. Tap again for a second one.
- 4 Open the cart: on a phone, the bar at the bottom; on a computer, it is already on the right.
- 5 Fix quantities with  / , remove with the bin icon, and type any instruction in **Note for the kitchen** — "no onion", "less spicy".
- 6 Tap . The kitchen sees it within 5 seconds.

The cart has two halves

Not sent yet

Still on your phone. You can change or delete anything here freely.

Sent to the order

Already with the kitchen and on the bill. It cannot be edited from here.

The customer wants one more thing

This is the most common thing that happens, and it is fully supported at any point until the bill is settled. A second round of drinks, an extra roti, a parcel on the way out — all the same steps:

- 1 Tap the same table again (it will say ).
- 2 Add the new dishes.
- 3 Press **Fire KOT** again.

The kitchen gets a **fresh ticket with only the new items** — the first round is never sent twice. Everything lands on one bill at the end.

Two things staff notice

While there are unsent items the tile goes back to  — the kitchen has not lost the first round, it just means something is waiting to be fired. And

Settle & bill

stays greyed out until you fire, so nobody bills food the kitchen never received. Waiters, cashiers, managers and owners can all do this.

Your phone locking will not lose the order

Items you have added but not yet sent are saved on the device. Unlock, reopen Odr, and they are still there.

Opened a table by mistake?

A manager or owner taps **Void order** at the bottom of the cart and confirms. The table goes back to Free. A voided order is never billed.

SECTION 05

The kitchen screen

Put it on a tablet or a TV near the pass and leave it running.

Every fired KOT appears as a card, oldest first, and refreshes itself every 5 seconds. Nobody needs to touch a keyboard.

What is on a card

- The **table number**, big enough to read across the kitchen.
- The ticket number, e.g. K0T-0004 , and a **QR** or **ZOMATO** badge if it did not come from a waiter.
- Each dish with its quantity, and any note marked *.
- The minutes since it was fired, and a coloured bar down the left edge.

The colour bar

Green	Under 5 minutes — just came in.
Amber	Under 12 minutes — should be moving.
Red	12 minutes or more — this table is waiting.

Clearing a ticket

When the food goes out, tap the big **Done** button. The card disappears. If you tap it by mistake the waiter can still see everything on the order — nothing is lost, the ticket just leaves the kitchen list.

SECTION 06

The bill

Settle, print, take the money at the counter.

- 1 Open the table and press **Settle & bill**.
- 2 The bill appears with GST worked out for you.
- 3 Press **Print** to print on any printer connected to the device, or **Kitchen printer** to send it straight to the thermal printer over Wi-Fi.
- 4 Collect payment at the counter. The table is free again.

What is on the bill

- Restaurant name, address and GSTIN.
- An invoice number that never repeats, e.g. `CS/2026-27/00004`.
- Every dish with quantity and line total.
- CGST and SGST shown **separately for each tax rate**. A 5% dish and a 12% dish get their own lines — that is what GST requires.
- The grand total.

If the printer does not answer

You will see "No printer answered". Check the printer is on and on the same Wi-Fi, then use the ordinary Print button instead. The bill is already saved either way — nothing is lost.

Paper size

Odr prints for the roll you actually own: a 58 mm roll or an 80 mm roll. Set it once in Settings and every bill and KOT comes out the right width.

SECTION 07

Parcels, Zomato and Swiggy

Orders with no table go through the same kitchen and the same bill.

- 1 On the Tables screen tap **Off-table** .
- 2 Choose **Parcel**, **Zomato**, **Swiggy** or **Other**.
- 3 Type the customer's name (for a parcel) or the app's order reference (for Zomato and Swiggy).
- 4 Tap **Start order** and add dishes exactly like a table.

It then appears in the **Off-table** strip on the floor screen with a coloured badge, and the kitchen sees the same badge on the ticket so they know it is going into a box, not onto a plate.

Zomato and Swiggy are typed in by hand

Odr does not connect to their systems. Someone reads the order off the tablet and enters it here. The benefit is that everything — dine-in, parcel, aggregator — ends up in one kitchen queue and one set of numbers.

SECTION 08

QR ordering

The diner's own phone becomes the menu. Nothing to download.

What the diner does

- 1 Points the phone camera at the QR card on the table.
- 2 The menu opens, showing the restaurant's name and their table number.
- 3 They browse by category, see the veg / non-veg square on every dish, and tap **Add**.
- 4 They review the cart, can add a note, then confirm.
- 5 They get a short order code and the message "*Pay at the counter*".

What you see

The order appears on the floor screen on that diner's table with a green **QR** badge, and the dishes go to the kitchen the moment the waiter fires the KOT. You settle and print it like any other table.

Prices cannot be tampered with

The phone only sends which dish and how many. Every price and name comes from your menu on the server. A diner cannot change what anything costs.

Putting the codes on the tables

- 1 Owner or manager opens **Settings** → **Table QR codes**.
- 2 Taps **Generate codes** — one unique code per table.
- 3 Taps **Print sheet** for an A4 page of cards, three to a row.
- 4 Cut along the dotted lines and stand one on each table. Laminating them is worth it.

Print the cards once

Every card is tied to its table. Print them after your tables are named the way you want them, so you do not have to reprint.

SECTION 09

Settings

Owners and managers only. Set it up once on day one.

Outlet

The outlet's name, GSTIN, address and invoice prefix — exactly what prints at the top of every bill. Each outlet has its own. Change them here and the next bill uses the new details.

Tables

Type a range and Odr fills in the rest. `T-1 to T-12` creates twelve tables. A comma list also works: `Bar-1, Bar-2, Window`. It shows you what it is about to add before you commit. The bin icon removes one.

Table QR codes

See Section 08. Generate, then print the sheet.

Printing

Paper width	58 mm or 80 mm — match the roll you buy.
--------------------	--

Kitchen printer IP	The printer's address on your Wi-Fi, e.g. <code>192.168.1.50</code> . Leave blank if you only print through the browser.
---------------------------	--

Port	Almost always <code>9100</code> . Leave it alone unless told otherwise.
-------------	---

Test print	Checks the printer answers, before a real bill depends on it.
-------------------	---

Staff

Shows everyone who can sign in. To add someone, fill in their name, email, a password of at least 8 characters, and pick a role (see Section 02). Give people the smallest role that lets them do their job. For a captain, cashier or kitchen login you also pick **Works at** — the outlet they belong to. Owners and managers see every outlet, so there is nothing to pick.

Removing someone. When a staff member leaves, tap the bin next to their name. They can no longer sign in. Their past orders and bills stay exactly as they were — nothing in your records changes.

Owner only	Adding and removing staff. A manager can see the list but not change it.
-------------------	--

Yourself	Cannot be removed — it would lock you out of your own restaurant.
-----------------	---

The last owner	Cannot be removed — somebody has to be able to manage the place.
-----------------------	--

When someone leaves, remove them the same day

Their login works until you do. This is the one setting worth treating as security rather than housekeeping.

Menu

The menu has its own screen — see Section 10. Odr loads your first menu when you join; after that you change it yourself.

SECTION 10

Editing your menu

Owners and managers. One board, one tap for the thing you do daily.

Open **Menu** from the side bar. Each section of your menu — Dosa, Drinks, Snacks — is its own row of dish cards, laid out like the board on the wall. Every change is live for waiters and diners the moment you save.

Sold out — the one you will use every day

- 1 Open **Menu**.
- 2 Find the dish and tap **Sold out**.

That is it. The dish disappears from the diner's QR menu and from the waiter's order pad straight away, and a diner who still has it in their cart is told it is unavailable rather than being billed for it. On the board the card stays put, greyed with a **SOLD OUT** tag, so the kitchen can see at a glance what is off. Tap **Back on** when it returns.

With several outlets sharing one menu, sold out applies to **the outlet you are in** only. The dish stays on sale at your other outlets.

Changing a price or a name

- 1 Tap the dish card.
- 2 Edit the name, price, GST rate, description or veg / non-veg.
- 3 **Save**. New orders use the new price immediately.

Bills already printed do not change

Every order stores the price it was sold at. Editing a dish never rewrites yesterday's takings.

Adding and removing

New dish	Tap Add dish at the end of a section.
New section	Type the name at the top right and tap Section .
Rename a section	Tap its title and type over it.
Delete a dish	Open the dish → Delete this dish . Past bills are untouched.
Delete a section	Only possible once it is empty — so a mis-tap cannot wipe half the menu.

Photograph a printed menu to load it in bulk

For a big change, send Odr the menu and they import it in one go. Re-importing a menu with corrected prices *updates* the existing dishes — it will not leave you with each dish listed twice.

SECTION 11

When something goes wrong

Almost everything is fixed by reloading. Your orders live on the server, not on the phone.

WHAT YOU SEE	WHAT TO DO
"Working offline"	The internet dropped. Check the Wi-Fi. Items you have added but not sent are safe; send them once it is back.
Sent back to Sign in	The shift session expired. Sign in again — nothing is lost.
"Something broke on this screen"	Tap Reload . If it comes straight back, tap Sign out and sign in again.
"Subscription ended"	Contact Odr to renew. No orders can be taken until it is.
"No printer answered"	Printer off, or on a different Wi-Fi. Use the plain Print button meanwhile.
A table is stuck occupied	Manager opens it and taps Void order .
"No tables yet"	Nobody has added the tables. Owner does it in Settings.
Diner says the QR does not work	Serve them the normal way, then check the card is the one printed for that table.

The golden rule

Anything that was fired or settled is stored on the server. Losing, dropping or reloading a phone never loses an order.

QUICK CARD

One page for the wall

Print this page and stick it behind the counter.

Waiter

Seat a table	Tap the FREE tile.
Add dishes	Tap + . Search finds anything on the menu.
Special request	Type it in the note box on that line.
Send to kitchen	Fire KOT.
Customer wants more	Same table, add, Fire KOT again. Only the new items go to the kitchen.
Parcel / Zomato	Off-table button, top right.

Cashier

Make the bill	Open the table → Settle & bill.
Print it	Print , or Kitchen printer for the thermal one.
Payment	Taken at the counter. Odr does not handle money.

Kitchen

Read the card	Table number, dishes, notes marked * .
Red bar	12+ minutes. Push it out.
Food is out	Tap Done.

Owner

Add tables	Settings → type T-1 to T-12 .
Table QR codes	Settings → Generate → Print sheet → cut & place.
Printer	Settings → paper width, IP, Test print.
Add staff	Settings → Staff → name, email, password, role, and the outlet they work at.
Another outlet	Tap the outlet name in the top bar → pick it.
Sales for all outlets	Sales → All outlets.
Outlet details on the bill	Settings → Outlet → name, GSTIN, address, invoice prefix.
Someone left	Settings → Staff → bin icon next to their name.
Dish is finished	Menu → tap Sold out on the card.
Change a price	Menu → tap the dish → edit → Save.
Cancel an order	Open it → Void order.

Working alone

Use the owner login. It can do everything.

Odr · Made in Mangaluru · Version 1.1 · FY 2026–27

Powered by **zowcode.com** · Questions? hello@zowcode.com