

File permissions can also be edited by right-clicking on a file, accessing Permissions under the Properties section and clicking on Access Control. Then set the users who are allowed to access and work on the file.

```

• #!/bin/bash
• # Archive the input file to a predetermined location
• # Check we have exactly 1 argument
• if [ $# -ne 1 ]
• then
•     echo "Usage: $0 FILE"
•     exit 1 # Quit the script, indicate an error to the
shell
• fi
• # The archive location
• DATE=`date +%Y-%m-%d`
• archive=/home/pi/archives/$DATE
• # Make the destination if it does not already exist
• mkdir -p $archive
• # Copy the input file/directory

```

Building Desktop Applications-DIY

File permissions and information for all other systems are obtained by sending arguments to the mainframe. These are nothing but pieces of information that are passed into a program or function. When you issue a command like `cd /home/pi`, here the command is `cd` with one argument, `/home/pi`.

Desktop App

The following code is an introductory DIY to creating a template text box where the user can enter an input using a prompt. Remember to toggle the necessary switches and LED tabs on the mainboard before executing the code. But you can also have the program run on a headless mode without the need of any working monitor output:-

```

• ## Toggle an LED when the GUI button is pressed ##
• from tkinter import *
• import tkinter.font
• from gpiozero import LED
• import RPi.GPIO
• RPi.GPIO.setmode(RPi.GPIO.BCM)
•

```