TP9 ESP_IO
TP10 USB_D_P
TP11 USB_D_N
TP12 ESP_EN
R1 1k D2_A LED_R
R2 1k LED_G D3_A
R3 1k D4_A LED_B
TP5 I2C_MAIN_SDA
TP6 I2C_MAIN_SCL
TP7 I2S_BCLK
TP8 I2S_WS
D2 LTST-C193KRKT-5A GND LED_R
D3 LTST-C193KGKT-5A
D4 LTST-C193TBKT-5A GND LED_B
TP1 GND
TP2 3V3
TP3 VSYS
TP4 VDOCK
C1 100n +3V3 GND
R4 2.2k +3V3 I2C_MAIN_SDA
R5 2.2k +3V3 I2C_MAIN_SCL
C10 100n +3V3_FPC GND
C11 100n +3V3_FPC
C12 100n +3V3_FPC GND
U7 SHT45-AD1B-R2 I2C_MAIN_SDA I2C_MAIN_SCL SDA SCL VSS VDD GND +3V3
MIC1 ICS-43434 +3V3 GND LR VDD SCK WS SD I2S_BCLK I2S_WS I2S_SD_EXT
U4 TCA9546APWR A0 A1 RESET# SD0 SC0 SD1 SC1 GND VCC SDA SCL A2 SC3 SD3 SC2 SD2 GND DOCK_SDA DOCK_SCL +3V3 I2C_MAIN_SDA I2C_MAIN_SCL
D5 TPD4E05U06DQAR D1+ D1- GND D2+ D2- NC GND DOCK_D1_P DOCK_D1_N DOCK_D2_P DOCK_D2_N
J3 KH-A2009-2X06AB GND VDOCK +3V3_FPC DOCK_SDA DOCK_SCL DOCK_BCLK DOCK_WS DOCK_SD DOCK_PRESENT_ID
J2 FH34SRJ-12S-0.5SH(50) GND VDOCK +3V3_FPC DOCK_SDA DOCK_SCL DOCK_BCLK DOCK_WS DOCK_SD DOCK_PRESENT_ID
U8 SHT45-AD1B-R2 DOCK_SDA DOCK_SCL SDA SCL VSS VDD GND +3V3_FPC
MIC2 ICS-43434 +3V3_FPC GND LR VDD SCK WS SD DOCK_BCLK DOCK_WS DOCK_SD
U9 ICM-42688-P AP_SDO/AP_AD0 RESV INT1/INT VDDIO GND AP_SDA/AP_SDIO/AP_SDI AP_SCL/AP_SCLK AP_CS INT2/FSYNC/CLKIN VDD SPI_MISO IMU_INT +3V3 GND SPI_MOSI SPI_SCLK IMU_CS +3V3
R6 5.1k USB_CC1 GND
R7 5.1k GND USB_CC2
C? 10uF VBUS_USB GND
C? 10nF GND VBUS_USB
R11 1.78k GND CHARGER_ISET
R12 1.54k GND EXT_ILIM
R13 46.4k GND CHARGER_TMR
L1 2.2u SW +3V3
R14 316k FB_3V3 +3V3
R15 100k GND FB_3V3
C? 100n +3V3 GND
C2 1u GND +3V3
U2 BQ24074RGTR IN ILIM ITERM ISET TS BAT OUT CHG# PGOOD# EN1 EN2 TMR CE# EP VSS VIN_CHARGER CHARGER_ILIM CHARGER_ITERM CHARGER_ISET BATT_TS VBAT VSYS CHARGER_CHG CHARGER_PGOOD +3V3 GND CHARGER_TMR
U6 TPS26600RHF N.C EP OUT FLT# dVdT ILIM IMON GND RTN SHDN# MODE VIN_EXT_PROTECTED EXT_FLT EXT_DVDT EXT_ILIM EXT_IMON EXT_SHDN EXT_MODE VIN_EXT_RAW EXT_UVLO EXT_OVP
U11 TPS2121RUXR OUT VIN_CHARGER VIN_EXT_PROTECTED PWRMUX_CP2 PWRMUX_OV2 PWRMUX_OV1 PWRMUX_PR1 GND SS ILM ST OUT IN1 PWRMUX_SS PWRMUX_ILM PWRMUX_ST VBUS_USB
J1 TYPE-C-31-M-12 GND VBUS SBU2 CC1 DN2 DP1 DN1 DP2 SBU1 CC2 EH USB_CC1 USB_CC2 USB_D_P USB_D_N VBUS_USB
D6 USBLC6-2SC6 USB_D_P USB_D_N GND
U3 TPS62162DSGR VIN EN PG SW VOS FB EP AGND PGND VSYS REG_EN REG_PG BUCK_SW +3V3 FB_3V3 GND
J4 XY-S2B-PH-SM4-TB VBAT GND
Q1 TPS22919DCKR IN GND ON VOUT QOD NC VSYS DOCK_EN VDOCK
U1 ESP32-S3-WROOM-1-N16R8 GND 3V3 EN IO4 IO5 IO6 IO7 IO15 IO16 IO17 IO18 IO8 IO19 IO20 IO3 IO46 IO9 IO10 IO11 IO12 IO13 IO14 IO21 IO47 IO48 IO45 IO0 IO35 IO36 IO37 IO38 IO39 IO40 IO41 IO42 RXD0 TXD0 IO2 IO1
+3V3 ESP_EN I2C_MAIN_SDA I2C_MAIN_SCL SPI_SCLK SPI_MOSI UART1_RX UART1_TX SPI_MISO USB_D_N USB_D_P SD_CS I2S_BCLK I2S_WS I2S_SD DOCK_PRESENT_ID LED_R LED_B DEBUG_TX DEBUG_RX LED_G AUDIO_SEL ESP_BOOT
U12 SN74LVC1G3157DBVR-JSM NO GND NC IN VCC COM I2S_SD_EXT DOCK_SD AUDIO_SEL +3V3 I2S_SD