



Visited all 115 discovered charts with --filter, four workers, and a five-minute test budget per chart. No scan-wide deadline was imposed.

Recorded 19,612 test attempts in 42.3 minutes. Attempts include shrinking and repeated inputs; they are not counts of unique inputs or confirmed bugs.

Findings: 113 failed; 1 skipped-library; 1 time-limit.

known-inputs: 113 failed; 1 time-limit.

robustness: 12 failed; 96 passed; 6 time-limit.

Observed failures include chart validation rejections, rendering failures, and possible tooling limitations. Inferred inputs are not an authoritative chart contract. Findings need triage before being called chart defects; time-limited coverage remains incomplete.

Checks: dependency build in isolated copies, Helm lint, Helm template with values-schema checks, and built-in manifest checks. External kubeconform/kubesecc validation was not configured.

Source: third_party/bitnami-charts at 6a8cccf3c29a1faabf0c34c8276a09ed14f3c5b3; Helm 4.3.0. Per-worker dependency caches are isolated.

Each primary chart has one dedicated job; nested results from parent jobs are retained separately and excluded from totals.

[Combined PDF](#) · [Aggregate data](#) · [Raw logs and provenance](#)

Directory: third_party/bitnami-charts
Started (Unix epoch): 1789260967
Elapsed: 2539.00 seconds
Charts discovered: 115
Scan status: completed
Discovery complete: True
Unstarted charts: 0

Results describe the tested sample; they do not prove chart correctness.

Baseline-only, skipped, blocked, and incomplete charts are not property-test passes.

Status counts

```
{
  "failed": 113,
  "skipped-library": 1,
  "time-limit": 1
}
```

Settings

```
{
  "max_examples": 100,
  "filter": true,
  "fail": false,
  "permutations": null,
  "chart_timeout_seconds": 300.0,
  "scan_timeout_seconds": null,
  "helm": "Helm 4.3.0",
  "seed": 0,
  "build_dependencies": true,
  "values": "values.yaml",
  "clone_timeout_seconds": 180,
  "workers": 4,
```



```
"external_conformity": false
}
```

Errors

115 distinct diagnostics across 125 occurrences; 10 repeats grouped.
Matching diagnostics do not establish a shared root cause.

E001

Error: YAML parse error on apache/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/apache \(known-inputs; failed\)](#)

E002

Error: YAML parse error on apache/templates/svc.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/apache \(robustness; failed\)](#)

E003

Error: YAML parse error on apisix/templates/control-plane/api-token-secret.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/apisix \(known-inputs; failed\)](#)

E004

Error: YAML parse error on appsmith/templates/backend/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/appsmith \(known-inputs; failed\)](#)

E005

Error: YAML parse error on argo-cd/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/argo-cd \(known-inputs; failed\)](#)

E006

Error: YAML parse error on argo-workflows/templates/controller/deployment.yaml: error converting YAML to JSON: yaml: line 30: mapping values are not allowed in this context

- [bitnami/argo-workflows \(known-inputs; failed\)](#)

E007

Error: YAML parse error on cassandra/templates/statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/cassandra \(known-inputs; failed\)](#)

E008

Error: YAML parse error on cert-manager/templates/cainjector/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/cert-manager \(known-inputs; failed\)](#)

E009

Error: YAML parse error on clickhouse/templates/configd-configmap.yaml: error converting YAML to JSON: yaml: line 14: did not find expected key

- [bitnami/clickhouse \(known-inputs; failed\)](#)



E010

Error: YAML parse error on cloudnative-pg/templates/operator/clusterrolebinding.yaml: error converting YAML to JSON: yaml: line 4: did not find expected comment or line break

- [bitnami/cloudnative-pg \(known-inputs; failed\)](#)

E011

Error: YAML parse error on consul/templates/statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/consul \(known-inputs; failed\)](#)

E012

Error: YAML parse error on contour/templates/certgen/serviceaccount.yaml: error converting YAML to JSON: yaml: line 15: did not find expected key

- [bitnami/contour \(known-inputs; failed\)](#)

E013

Error: YAML parse error on deepspeed/templates/client/client-dep-job.yaml: error converting YAML to JSON: yaml: line 31: did not find expected key

- [bitnami/deepspeed \(known-inputs; failed\)](#)

E014

Error: YAML parse error on discourse/templates/service.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go struct field .metadata.annotations. of type string

- [bitnami/discourse \(known-inputs; failed\)](#)

E015

Error: YAML parse error on dremio/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/dremio \(known-inputs; failed\)](#)

E016

Error: YAML parse error on ejbca/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/ejbca \(known-inputs; failed\)](#)

E017

Error: YAML parse error on elasticsearch/templates/coordinating/statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/elasticsearch \(known-inputs; failed\)](#)

E018

Error: YAML parse error on envoy-gateway/templates/deployment.yaml: error converting YAML to JSON: yaml: line 37: did not find expected key

- [bitnami/envoy-gateway \(known-inputs; failed\)](#)

E019

Error: YAML parse error on etcd/templates/svc-headless.yaml: error converting YAML to JSON: yaml: line 14: did not find expected key

- [bitnami/etcd \(known-inputs; failed\)](#)



E020

Error: YAML parse error on external-dns/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/external-dns \(known-inputs; failed\)](#)

E021

Error: YAML parse error on flink/templates/taskmanager/statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/flink \(known-inputs; failed\)](#)

E022

Error: YAML parse error on fluent-bit/templates/configmap.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/fluent-bit \(known-inputs; failed\)](#)

E023

Error: YAML parse error on fluentd/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/fluentd \(known-inputs; failed\)](#)

E024

Error: YAML parse error on flux/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/flux \(known-inputs; failed\)](#)

E025

Error: YAML parse error on gitea/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/gitea \(known-inputs; failed\)](#)

E026

Error: YAML parse error on gitlab-runner/templates/configmap.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/gitlab-runner \(known-inputs; failed\)](#)

E027

Error: YAML parse error on grafana-k6-operator/templates/deployment.yaml: error converting YAML to JSON: yaml: line 85: mapping keys are not allowed in this context

- [bitnami/grafana-k6-operator \(known-inputs; failed\)](#)

E028

Error: YAML parse error on grafana-loki/templates/gateway/configmap-http.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/grafana-loki \(known-inputs; failed\)](#)

E029

Error: YAML parse error on grafana-operator/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/grafana-operator \(known-inputs; failed\)](#)



E030

Error: YAML parse error on grafana-tempo/templates/tempo-configmap.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/grafana-tempo \(known-inputs; failed\)](#)

E031

Error: YAML parse error on grafana/templates/application.yaml: error converting YAML to JSON: yaml: line 138: mapping keys are not allowed in this context

- [bitnami/grafana \(known-inputs; failed\)](#)

E032

Error: YAML parse error on haproxy/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/haproxy \(known-inputs; failed\)](#)

E033

Error: YAML parse error on harbor/templates/core/core-dpl.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/harbor \(known-inputs; failed\)](#)

E034

Error: YAML parse error on jaeger/templates/collector/configmap.yaml: error converting YAML to JSON: yaml: line 86: found unexpected end of stream

- [bitnami/jaeger \(known-inputs; failed\)](#)

E035

Error: YAML parse error on janusgraph/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/janusgraph \(known-inputs; failed\)](#)

E036

Error: YAML parse error on jenkins/templates/controller-svc.yaml: error converting YAML to JSON: yaml: line 13: mapping values are not allowed in this context

- [bitnami/jenkins \(robustness; failed\)](#)

E037

Error: YAML parse error on kafka/templates/controller-eligible/statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/kafka \(known-inputs; failed\)](#)

E038

Error: YAML parse error on kibana/templates/ingress.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/kibana \(known-inputs; failed\)](#)

E039

Error: YAML parse error on kong/templates/dep-ds.yaml: error converting YAML to JSON: yaml: line 58: block sequence entries are not allowed in this context

- [bitnami/kong \(known-inputs; failed\)](#)



E040

Error: YAML parse error on kube-arangodb/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/kube-arangodb \(known-inputs; failed\)](#)

E041

Error: YAML parse error on kuberay/templates/apiserver/clusterrolebinding.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go struct field .metadata.annotations. of type string

- [bitnami/kuberay \(known-inputs; failed\)](#)

E042

Error: YAML parse error on kubernetes-event-exporter/templates/deployment.yaml: error converting YAML to JSON: yaml: line 27: did not find expected key

- [bitnami/kubernetes-event-exporter \(known-inputs; failed\)](#)

E043

Error: YAML parse error on logstash/templates/sts.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/logstash \(known-inputs; failed\)](#)

E044

Error: YAML parse error on matomo/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/matomo \(known-inputs; failed\)](#)

E045

Error: YAML parse error on metallb/templates/controller/configmap.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go struct field .metadata.annotations. of type string

- [bitnami/metallb \(known-inputs; failed\)](#)

E046

Error: YAML parse error on metrics-server/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/metrics-server \(known-inputs; failed\)](#)

E047

Error: YAML parse error on mlflow/templates/run/dep-job.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/mlflow \(robustness; failed\)](#)

E048

Error: YAML parse error on mongodb-sharded/templates/config-server/config-server-statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/mongodb-sharded \(known-inputs; failed\)](#)

E049

Error: YAML parse error on mongodb/templates/configmap.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/mongodb \(known-inputs; failed\)](#)



E050

Error: YAML parse error on moodle/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/moodle \(known-inputs; failed\)](#)

E051

Error: YAML parse error on multus-cni/templates/daemonset.yaml: error converting YAML to JSON: yaml: line 73: did not find expected comment or line break

- [bitnami/multus-cni \(known-inputs; failed\)](#)

E052

Error: YAML parse error on mysql/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/mysql \(known-inputs; failed\)](#)

E053

Error: YAML parse error on nats/templates/application.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/nats \(known-inputs; failed\)](#)

E054

Error: YAML parse error on nessie/templates/networkpolicy.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go struct field .metadata.annotations. of type string

- [bitnami/nessie \(known-inputs; failed\)](#)

E055

Error: YAML parse error on nginx/templates/context-includes-configmap.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/nginx \(robustness; failed\)](#)

E056

Error: YAML parse error on nginx/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/nginx \(known-inputs; failed\)](#)

E057

Error: YAML parse error on opensearch/templates/coordinating/statefulset.yaml: error converting YAML to JSON: yaml: line 184: mapping values are not allowed in this context

- [bitnami/opensearch \(known-inputs; failed\)](#)

E058

Error: YAML parse error on parse/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/parse \(known-inputs; failed\)](#)

E059

Error: YAML parse error on pinniped/templates/concierge/apiservice-identity.yaml: error converting YAML to JSON: yaml: line 23: found unexpected end of stream

- [bitnami/pinniped \(known-inputs; failed\)](#)



E060

Error: YAML parse error on postgresql-ha/templates/pgpool/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/postgresql-ha \(known-inputs; failed\)](#)

E061

Error: YAML parse error on postgresql/templates/primary/statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/postgresql \(robustness; failed\)](#)

E062

Error: YAML parse error on prometheus/templates/alertmanager/networkpolicy.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/prometheus \(known-inputs; failed\)](#)

E063

Error: YAML parse error on prometheus/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/prometheus \(robustness; failed\)](#)

E064

Error: YAML parse error on rabbitmq-cluster-operator/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/rabbitmq-cluster-operator \(known-inputs; failed\)](#)

E065

Error: YAML parse error on rabbitmq/templates/statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/rabbitmq \(known-inputs; failed\)](#)

E066

Error: YAML parse error on redis-cluster/templates/redis-statefulset.yaml: error converting YAML to JSON: yaml: line 177: block sequence entries are not allowed in this context

- [bitnami/redis-cluster \(known-inputs; failed\)](#)

E067

Error: YAML parse error on redmine/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/redmine \(known-inputs; failed\)](#)

E068

Error: YAML parse error on redmine/templates/svc.yaml: error converting YAML to JSON: yaml: line 14: block sequence entries are not allowed in this context

- [bitnami/redmine \(robustness; failed\)](#)

E069

Error: YAML parse error on seaweedfs/templates/filer/statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/seaweedfs \(known-inputs; failed\)](#)



E070

Error: YAML parse error on solr/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/solr \(known-inputs; failed\)](#)

E071

Error: YAML parse error on sonarqube/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/sonarqube \(known-inputs; failed\)](#)

E072

Error: YAML parse error on superset/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/superset \(known-inputs; failed\)](#)

E073

Error: YAML parse error on tensorflow-resnet/templates/service.yaml: error converting YAML to JSON: yaml: line 15: mapping values are not allowed in this context

- [bitnami/tensorflow-resnet \(known-inputs; failed\)](#)

E074

Error: YAML parse error on thanos/templates/storegateway/configmap.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/thanos \(known-inputs; failed\)](#)

E075

Error: YAML parse error on tomcat/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/tomcat \(known-inputs; failed\)](#)

E076

Error: YAML parse error on valkey-cluster/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/valkey-cluster \(known-inputs; failed\)](#)

E077

Error: YAML parse error on valkey/templates/replicas/application.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/valkey \(known-inputs; failed\)](#)

E078

Error: YAML parse error on vault/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/vault \(known-inputs; failed\)](#)

E079

Error: YAML parse error on victoriametrics/templates/vmagent/dep-ds.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/victoriametrics \(known-inputs; failed\)](#)



E080

Error: YAML parse error on wordpress/templates/httpd-configmap.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/wordpress \(known-inputs; failed\)](#)

E081

Error: YAML parse error on wordpress/templates/svc.yaml: error converting YAML to JSON: yaml: line 13: mapping keys are not allowed in this context

- [bitnami/wordpress \(robustness; failed\)](#)

E082

Error: YAML parse error on zookeeper/templates/statefulset.yaml: error converting YAML to JSON: yaml: line 181: block sequence entries are not allowed in this context

- [bitnami/zookeeper \(known-inputs; failed\)](#)

E083

Error: mlflow/templates/tracking/deployment.yaml:105:12
executing "mlflow/templates/tracking/deployment.yaml" at <include
"mlflow.v0.volumePermissionsInitContainer" .>:
error calling include:
mlflow/templates/_helpers.tpl:553:12
executing "mlflow.v0.volumePermissionsInitContainer" at <include>:
wrong number of args for include: want 2 got 1

- [bitnami/mlflow \(known-inputs; failed\)](#)

E084

Error: schema-registry/templates/http-route.yaml:7:13
executing "schema-registry/templates/http-route.yaml" at <\$route.enabled>:
nil pointer evaluating interface {}.enabled

- [bitnami/schema-registry \(known-inputs; failed\)](#)

E085

Error: scylladb/templates/networkpolicy.yaml:62:19
executing "scylladb/templates/networkpolicy.yaml" at <.containerPort>:
nil pointer evaluating interface {}.containerPort

- [bitnami/scylladb \(known-inputs; failed\)](#)

E086

Error: values don't meet the specifications of the schema(s) in the following chart(s):
mysql:

- at '/architecture': value must be one of 'standalone', 'replication'

- [bitnami/ghost \(known-inputs; failed\)](#)

E087

chart rendered no resources (use allow_empty explicitly)

- [bitnami/kube-prometheus/charts/kube-prometheus-crds \(known-inputs; failed\)](#)
- [bitnami/kube-prometheus/charts/kube-prometheus-crds \(robustness; failed\)](#)



E088

duplicate resource: ('rbac.authorization.k8s.io/v1', 'Role', None, 'hypothesis-clickhouse-operator')

- [bitnami/clickhouse-operator \(known-inputs; failed\)](#)

E089

Source: airflow 25.1.0 / templates/NOTES.txt

execution error at (airflow/templates/NOTES.txt:129:3):

VALUES VALIDATION:

airflow: executors

You need to provide at least one value for the '.executor' parameter.

- [bitnami/airflow \(known-inputs; failed\)](#)

E090

Source: aspnet-core 8.0.0 / templates/NOTES.txt

execution error at (aspnet-core/templates/NOTES.txt:58:4):

VALUES VALIDATION:

aspnet-core: missing-extra-volume-mounts

You specified extra volumes but not mount points for them.

Please also set the extraVolumeMounts parameter.

- [bitnami/aspnet-core \(known-inputs; failed\)](#)

E091

Source: cadvisor 0.1.14 / templates/daemonset.yaml

execution error at (cadvisor/templates/daemonset.yaml:155:25): ERROR: Preset key '' invalid. Allowed values are xlarge,2xlarge,nano,micro,small,medium,large

- [bitnami/cadvisor \(known-inputs; failed\)](#)

E092

Source: chainloop 4.0.76 / templates/controlplane/secret-jwt-cas-private-key.yaml

execution error at (chainloop/templates/controlplane/secret-jwt-cas-private-key.yaml:14:22):

Authentication Private Key "casJWTPrivateKey" required

- [bitnami/chainloop \(known-inputs; failed\)](#)

E093

Source: grafana-alloy 1.0.8 / templates/NOTES.txt

execution error at (grafana-alloy/templates/NOTES.txt:71:4):

\u26a0 ERROR: Original containers have been substituted for unrecognized ones. Deploying this chart with non-standard containers is likely to cause degraded security and performance, broken chart features, and missing environment variables.

Unrecognized images:

- 00/bitnami/grafana-alloy:1.10.2-debian-12-r0

- 00/bitnami/configmap-reload:0.15.0-debian-12-r12

If you are sure you want to proceed with non-standard containers, you can skip container image verification by setting the global parameter 'global.security.allowInsecureImages' to true.

Further information can be obtained at <https://github.com/bitnami/charts/issues/30850>

- [bitnami/grafana-alloy \(known-inputs; failed\)](#)



E094

Source: influxdb 7.1.21 / templates/NOTES.txt

execution error at (influxdb/templates/NOTES.txt:146:4):

\u26a0 ERROR: Original containers have been substituted for unrecognized ones. Deploying this chart with non-standard containers is likely to cause degraded security and performance, broken chart features, and missing environment variables.

Unrecognized images:

- 00/bitnami/influxdb:3.4.1-debian-12-r0
- 00/bitnami/os-shell:12-debian-12-r51
- 00/bitnami/kubectrl:1.33.4-debian-12-r0

If you are sure you want to proceed with non-standard containers, you can skip container image verification by setting the global parameter 'global.security.allowInsecureImages' to true.

Further information can be obtained at <https://github.com/bitnami/charts/issues/30850>

- [bitnami/influxdb \(known-inputs; failed\)](#)

E095

Source: jupyterhub 10.0.6 / templates/proxy/deployment.yaml

execution error at (jupyterhub/templates/proxy/deployment.yaml:32:32): ERROR: Preset key '' invalid. Allowed values are medium, large, xlarge, 2xlarge, nano, micro, small

- [bitnami/jupyterhub \(known-inputs; failed\)](#)

E096

Source: kube-state-metrics 5.1.1 / templates/deployment.yaml

execution error at (kube-state-metrics/templates/deployment.yaml:205:25): ERROR: Preset key '' invalid. Allowed values are large, xlarge, 2xlarge, nano, micro, small, medium

- [bitnami/kube-state-metrics \(known-inputs; failed\)](#)

E097

Source: mariadb-galera 16.0.2 / templates/statefulset.yaml

execution error at (mariadb-galera/templates/statefulset.yaml:78:25): ERROR: Preset key '' invalid. Allowed values are nano, micro, small, medium, large, xlarge, 2xlarge

- [bitnami/mariadb-galera \(known-inputs; failed\)](#)

E098

Source: mariadb 22.0.0 / templates/NOTES.txt

execution error at (mariadb/templates/NOTES.txt:74:4):

VALUES VALIDATION:

mariadb: architecture

Invalid architecture selected. Valid values are "standalone" and "replication". Please set a valid architecture (--set architecture="xxxx")

- [bitnami/drupal \(known-inputs; failed\)](#)

E099

Source: mariadb 23.0.1 / templates/NOTES.txt

execution error at (mariadb/templates/NOTES.txt:74:4):

VALUES VALIDATION:

mariadb: architecture

Invalid architecture selected. Valid values are "standalone" and "replication". Please set a valid architecture (--set architecture="xxxx")

- [bitnami/mariadb \(known-inputs; failed\)](#)

- [bitnami/mariadb \(robustness; failed\)](#)



E100

Source: memcached 7.9.7 / templates/NOTES.txt

execution error at (memcached/templates/NOTES.txt:46:4):

VALUES VALIDATION:

memcached: architecture

Invalid architecture selected. Valid values are "standalone" and "high-availability". Please set a valid architecture (--set architecture="xxxx")

- [bitnami/grafana-mimir \(known-inputs; failed\)](#)

E101

Source: memcached 8.0.0 / templates/NOTES.txt

execution error at (memcached/templates/NOTES.txt:46:4):

VALUES VALIDATION:

memcached: architecture

Invalid architecture selected. Valid values are "standalone" and "high-availability". Please set a valid architecture (--set architecture="xxxx")

- [bitnami/memcached \(known-inputs; failed\)](#)

E102

Source: odoo 28.2.11 / templates/deployment.yaml

execution error at (odoo/templates/deployment.yaml:270:25): ERROR: Preset key '' invalid. Allowed values are large,xlarge,2xlarge,nano,micro,small,medium

- [bitnami/odoo \(known-inputs; failed\)](#)

E103

Source: postgresql 17.1.2 / templates/NOTES.txt

execution error at (postgresql/templates/NOTES.txt:118:4):

VALUES VALIDATION:

postgresql: psp.create, rbac.create

RBAC should be enabled if PSP is enabled in order for PSP to work.

More info at <https://kubernetes.io/docs/concepts/policy/pod-security-policy/#authorizing-policies>

- [bitnami/postgresql \(known-inputs; failed\)](#)

E104

Source: pytorch 5.0.0 / templates/NOTES.txt

execution error at (pytorch/templates/NOTES.txt:69:3):

VALUES VALIDATION:

pytorch: architecture

Invalid architecture selected. Valid values are "distributed" and "standalone". Please set a valid architecture (--set architecture="xxxx")

- [bitnami/pytorch \(known-inputs; failed\)](#)

E105

Source: redis 22.0.4 / templates/NOTES.txt

execution error at (redis/templates/NOTES.txt:202:4):

VALUES VALIDATION:

redis: architecture

Invalid architecture selected. Valid values are "standalone" and "replication". Please set a valid architecture (--set architecture="xxxx")

- [bitnami/oauth2-proxy \(known-inputs; failed\)](#)



E106

Source: redis 23.1.1 / templates/NOTES.txt

execution error at (redis/templates/NOTES.txt:202:4):

VALUES VALIDATION:

redis: architecture

Invalid architecture selected. Valid values are "standalone" and "replication". Please set a valid architecture (--set architecture="xxxx")

- [bitnami/redis \(known-inputs; failed\)](#)

- [bitnami/redis \(robustness; failed\)](#)

E107

Source: sealed-secrets 2.5.20 / templates/deployment.yaml

execution error at (sealed-secrets/templates/deployment.yaml:172:25): ERROR: Preset key '' invalid.

Allowed values are nano,micro,small,medium,large,xlarge,2xlarge

- [bitnami/sealed-secrets \(known-inputs; failed\)](#)

E108

Source: whereabouts 1.2.20 / templates/daemonset.yaml

execution error at (whereabouts/templates/daemonset.yaml:164:25): ERROR: Preset key '' invalid.

Allowed values are nano,micro,small,medium,large,xlarge,2xlarge

- [bitnami/whereabouts \(known-inputs; failed\)](#)

E109

invalid rendered YAML: more indented follow up line than first in a block scalar

in "<unicode string>", line 474, column 15:

set -o errexit

^ (line: 474)

- [bitnami/zipkin \(known-inputs; failed\)](#)

- [bitnami/zipkin \(robustness; failed\)](#)

E110

level=INFO msg="warning: destination for kube-state-metrics.rbac.rules is a table. Ignoring non-table value ([])"

Error: YAML parse error on kube-prometheus/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/kube-prometheus \(known-inputs; failed\)](#)

E111

level=INFO msg="warning: destination for postgresql.tls.autoGenerated is a table. Ignoring non-table value (false)"

Error: YAML parse error on keycloak/templates/statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/keycloak \(known-inputs; failed\)](#)

E112

resource has no metadata.name

- [bitnami/jenkins \(known-inputs; failed\)](#)

- [bitnami/keydb \(known-inputs; failed\)](#)

- [bitnami/mastodon \(known-inputs; failed\)](#)

- [bitnami/neo4j \(known-inputs; failed\)](#)

- [bitnami/phpmyadmin \(known-inputs; failed\)](#)

- [bitnami/spark \(known-inputs; failed\)](#)



- [bitnami/wildfly \(known-inputs; failed\)](#)

E113

Source: cilium 3.1.10 / templates/agent/daemonset.yaml

template: cilium/templates/agent/daemonset.yaml:30:15: executing

"cilium/templates/agent/daemonset.yaml" at <semverCompare "<1.30-0" (include

"common.capabilities.kubeVersion" .)>: error calling semverCompare: invalid semantic version

- [bitnami/cilium \(known-inputs; failed\)](#)

E114

Source: common 2.31.4 / templates/_capabilities.tpl

template: common/templates/_capabilities.tpl:131:32: executing "common.capabilities.psp.supported" at <semverCompare "<1.25-0" \$kubeVersion>: error calling semverCompare: invalid semantic version

- [bitnami/node-exporter \(known-inputs; failed\)](#)

E115

Source: concourse 5.1.47 / templates/worker/rolebinding.yaml

template: concourse/templates/worker/rolebinding.yaml:27:22: executing

"concourse/templates/worker/rolebinding.yaml" at <semverCompare "<1.25-0" (include

"common.capabilities.kubeVersion" .)>: error calling semverCompare: invalid semantic version

- [bitnami/concourse \(known-inputs; failed\)](#)

Charts

bitnami/airflow

Result: FAIL | Status: failed

Attempts: 145 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts 1789260948/runs/airflow 1789260968/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 506 | Varied in render attempts: 3

Missing values: 6 | Undocumented template fields: 534

Unreferenced values: 280 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 44

Phase robustness: passed | Attempts: 101

Errors: [E089](#)

Reproducing values (known-inputs):

```
{
  "executor": ""
}
```

bitnami/apache

Result: FAIL | Status: failed

Attempts: 212 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts 1789260948/runs/apache 1789260968/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 116 | Varied in render attempts: 30



Missing values: 2 | Undocumented template fields: 116
Unreferenced values: 41 (unknown)
Field variation does not prove branch or output coverage.
Phase known-inputs: failed | Attempts: 115
Phase robustness: failed | Attempts: 97
Errors: [E001](#), [E002](#)

Reproducing values (known-inputs):

```
{
  "nameOverride": "\u001f"
}
```

Reproducing values (robustness):

```
{
  "service": {
    "": [],
    "type": "\u001f"
  }
}
```

bitnami/apisix

Result: FAIL | Status: failed
Attempts: 85 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts:
[bitnami-runs/bitnami-charts 1789260948/runs/apisix 1789260968/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Identified input fields (lower bound): 369 | Varied in render attempts: 17
Missing values: 0 | Undocumented template fields: 37
Unreferenced values: 114 (unknown)
Field variation does not prove branch or output coverage.
Phase known-inputs: failed | Attempts: 52
Phase robustness: time-limit | Attempts: 33
Errors: [E003](#)

Reproducing values (known-inputs):

```
{
  "nameOverride": "\u001f"
}
```

bitnami/appsmith

Result: FAIL | Status: failed
Attempts: 136 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts:
[bitnami-runs/bitnami-charts 1789260948/runs/appsmith 1789260968/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Identified input fields (lower bound): 229 | Varied in render attempts: 2
Missing values: 0 | Undocumented template fields: 240
Unreferenced values: 120 (unknown)
Field variation does not prove branch or output coverage.
Phase known-inputs: failed | Attempts: 35



Phase robustness: passed | Attempts: 101

Errors: [E004](#)

Reproducing values (known-inputs):

```
{
  "nameOverride": "\u001f"
}
```

bitnami/argo-cd

Result: FAIL | Status: failed

Attempts: 162 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/argo-cd_1789261025/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 631 | Varied in render attempts: 7

Missing values: 26 | Undocumented template fields: 647

Unreferenced values: 240 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 61

Phase robustness: passed | Attempts: 101

Errors: [E005](#)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/argo-workflows

Result: FAIL | Status: failed

Attempts: 131 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/argo-workflows_1789261054/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 176 | Varied in render attempts: 0

Missing values: 0 | Undocumented template fields: 184

Unreferenced values: 91 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 30

Phase robustness: passed | Attempts: 101

Errors: [E006](#)

Reproducing values (known-inputs):

```
{
  "commonAnnotations": {
    "": null
  }
}
```



bitnami/aspnet-core

Result: FAIL | Status: failed

Attempts: 206 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/aspnet-core_1789261101/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 111 | Varied in render attempts: 38

Missing values: 5 | Undocumented template fields: 116

Unreferenced values: 33 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 105

Phase robustness: passed | Attempts: 101

Errors: [E090](#)

Reproducing values (known-inputs):

```
{
  "extraVolumes": [
    null
  ]
}
```

bitnami/cadvisor

Result: FAIL | Status: failed

Attempts: 126 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/cadvisor_1789261127/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 98 | Varied in render attempts: 2

Missing values: 3 | Undocumented template fields: 102

Unreferenced values: 34 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 25

Phase robustness: passed | Attempts: 101

Errors: [E091](#)

Reproducing values (known-inputs):

```
{
  "resourcesPreset": ""
}
```

bitnami/cassandra

Result: FAIL | Status: failed

Attempts: 135 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/cassandra_1789261132/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 131 | Varied in render attempts: 1



Missing values: 1 | Undocumented template fields: 137
Unreferenced values: 53 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 34

Phase robustness: passed | Attempts: 101

Errors: [E007](#)

Reproducing values (known-inputs):

```
{
  "extraEnvVarsCM": "\u001f"
}
```

bitnami/cert-manager

Result: FAIL | Status: failed

Attempts: 168 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/cert-manager_1789261145/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 186 | Varied in render attempts: 51

Missing values: 4 | Undocumented template fields: 195

Unreferenced values: 66 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 67

Phase robustness: passed | Attempts: 101

Errors: [E008](#)

Reproducing values (known-inputs):

```
{
  "leaderElection": {
    "namespace": "\u001f"
  }
}
```

bitnami/chainloop

Result: FAIL | Status: failed

Attempts: 147 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/chainloop_1789261157/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 331 | Varied in render attempts: 6

Missing values: 6 | Undocumented template fields: 346

Unreferenced values: 81 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 46

Phase robustness: passed | Attempts: 101

Errors: [E092](#)

Reproducing values (known-inputs):

```
{
  "development": false
}
```



```
}
```

bitnami/cilium

Result: FAIL | Status: failed

Attempts: 187 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/cilium_1789261173/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 456 | Varied in render attempts: 11

Missing values: 0 | Undocumented template fields: 478

Unreferenced values: 310 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 86

Phase robustness: passed | Attempts: 101

Errors: [E113](#)

Reproducing values (known-inputs):

```
{
  "kubeVersion": ":"
}
```

bitnami/clickhouse

Result: FAIL | Status: failed

Attempts: 181 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/clickhouse_1789261201/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 243 | Varied in render attempts: 24

Missing values: 0 | Undocumented template fields: 255

Unreferenced values: 84 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 80

Phase robustness: passed | Attempts: 101

Errors: [E009](#)

Reproducing values (known-inputs):

```
{
  "configdFiles": {
    "": null
  }
}
```

bitnami/clickhouse-operator

Result: FAIL | Status: failed

Attempts: 172 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/clickhouse-operator_1789261238/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed



Identified input fields (lower bound): 117 | Varied in render attempts: 10
Missing values: 0 | Undocumented template fields: 124
Unreferenced values: 56 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 71

Phase robustness: passed | Attempts: 101

Errors: [E088](#)

Reproducing values (known-inputs):

```
{
  "watchNamespaces": [
    null,
    null
  ]
}
```

bitnami/cloudnative-pg

Result: FAIL | Status: failed

Attempts: 152 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/cloudnative-pg_1789261278/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 227 | Varied in render attempts: 1

Missing values: 0 | Undocumented template fields: 235

Unreferenced values: 50 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 51

Phase robustness: passed | Attempts: 101

Errors: [E010](#)

Reproducing values (known-inputs):

```
{
  "fullnameOverride": ">"
}
```

bitnami/common

Result: N/A | Status: skipped-library

Attempts: N/A | Remaining iterations: unknown

Coverage: not a standalone application

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/common_1789261278/0000](#)

Filtering applied: False

Chart did not enter finite permutation testing

bitnami/concourse

Result: FAIL | Status: failed

Attempts: 158 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/concourse_1789261279/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed



Identified input fields (lower bound): 229 | Varied in render attempts: 1
Missing values: 5 | Undocumented template fields: 236
Unreferenced values: 76 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 57

Phase robustness: passed | Attempts: 101

Errors: [E115](#)

Reproducing values (known-inputs):

```
{
  "kubeVersion": ":"
}
```

bitnami/consul

Result: FAIL | Status: failed

Attempts: 140 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts 1789260948/runs/consul 1789261319/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 123 | Varied in render attempts: 3

Missing values: 2 | Undocumented template fields: 129

Unreferenced values: 38 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 39

Phase robustness: passed | Attempts: 101

Errors: [E011](#)

Reproducing values (known-inputs):

```
{
  "existingConfigmap": "\u001f"
}
```

bitnami/contour

Result: FAIL | Status: failed

Attempts: 120 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts 1789260948/runs/contour 1789261328/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 262 | Varied in render attempts: 3

Missing values: 3 | Undocumented template fields: 274

Unreferenced values: 141 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 19

Phase robustness: passed | Attempts: 101

Errors: [E012](#)

Reproducing values (known-inputs):

```
{
  "commonAnnotations": {
    "": null
  }
}
```



```
}  
}
```

bitnami/deepspeed

Result: FAIL | Status: failed
Attempts: 107 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts:
[bitnami-runs/bitnami-charts_1789260948/runs/deepspeed_1789261342/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Identified input fields (lower bound): 145 | Varied in render attempts: 9
Missing values: 1 | Undocumented template fields: 13
Unreferenced values: 71 (unknown)
Field variation does not prove branch or output coverage.
Phase known-inputs: failed | Attempts: 12
Phase robustness: time-limit | Attempts: 95
Errors: [E013](#)
Reproducing values (known-inputs):

```
{  
  "commonAnnotations": {  
    "": null  
  }  
}
```

bitnami/discourse

Result: FAIL | Status: failed
Attempts: 162 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts:
[bitnami-runs/bitnami-charts_1789260948/runs/discourse_1789261349/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Identified input fields (lower bound): 129 | Varied in render attempts: 12
Missing values: 1 | Undocumented template fields: 136
Unreferenced values: 74 (unknown)
Field variation does not prove branch or output coverage.
Phase known-inputs: failed | Attempts: 61
Phase robustness: passed | Attempts: 101
Errors: [E014](#)
Reproducing values (known-inputs):

```
{  
  "service": {  
    "annotations": {  
      "": []  
    }  
  }  
}
```



bitnami/dremio

Result: FAIL | Status: failed

Attempts: 147 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/dremio_1789261357/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 304 | Varied in render attempts: 28

Missing values: 7 | Undocumented template fields: 326

Unreferenced values: 137 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 46

Phase robustness: passed | Attempts: 101

Errors: [E015](#)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/drupal

Result: FAIL | Status: failed

Attempts: 131 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/drupal_1789261399/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 149 | Varied in render attempts: 21

Missing values: 6 | Undocumented template fields: 143

Unreferenced values: 48 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 30

Phase robustness: passed | Attempts: 101

Errors: [E098](#)

Reproducing values (known-inputs):

```
{
  "mariadb": {
    "architecture": ""
  }
}
```

bitnami/ejbca

Result: FAIL | Status: failed

Attempts: 147 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/ejbca_1789261434/0000](#)

Filtering applied: True



Generation order only; original-schema cases run last, not removed
Identified input fields (lower bound): 100 | Varied in render attempts: 4
Missing values: 4 | Undocumented template fields: 103
Unreferenced values: 52 (unknown)
Field variation does not prove branch or output coverage.
Phase known-inputs: failed | Attempts: 46
Phase robustness: passed | Attempts: 101
Errors: [E016](#)
Reproducing values (known-inputs):

```
{
  "ejbcaKeystoreExistingSecret": "\u001f"
}
```

bitnami/elasticsearch

Result: FAIL | Status: failed
Attempts: 143 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts:
[bitnami-runs/bitnami-charts_1789260948/runs/elasticsearch_1789261468/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Identified input fields (lower bound): 382 | Varied in render attempts: 5
Missing values: 0 | Undocumented template fields: 396
Unreferenced values: 180 (unknown)
Field variation does not prove branch or output coverage.
Phase known-inputs: failed | Attempts: 42
Phase robustness: passed | Attempts: 101
Errors: [E017](#)
Reproducing values (known-inputs):

```
{
  "clusterDomain": "\u001f"
}
```

bitnami/envoy-gateway

Result: FAIL | Status: failed
Attempts: 156 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts:
[bitnami-runs/bitnami-charts_1789260948/runs/envoy-gateway_1789261488/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Identified input fields (lower bound): 147 | Varied in render attempts: 9
Missing values: 0 | Undocumented template fields: 153
Unreferenced values: 55 (unknown)
Field variation does not prove branch or output coverage.
Phase known-inputs: failed | Attempts: 55
Phase robustness: passed | Attempts: 101
Errors: [E018](#)
Reproducing values (known-inputs):

```
{
```



```
"commonAnnotations": {  
  "": null  
}
```

bitnami/etcd

Result: FAIL | Status: failed
Attempts: 108 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts:
[bitnami-runs/bitnami-charts_1789260948/runs/etcd_1789261495/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Identified input fields (lower bound): 190 | Varied in render attempts: 26
Missing values: 1 | Undocumented template fields: 199
Unreferenced values: 58 (unknown)
Field variation does not prove branch or output coverage.
Phase known-inputs: failed | Attempts: 62
Phase robustness: time-limit | Attempts: 46
Errors: [E019](#)
Reproducing values (known-inputs):

```
{  
  "commonAnnotations": {  
    "": null  
  }  
}
```

bitnami/external-dns

Result: FAIL | Status: failed
Attempts: 148 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts:
[bitnami-runs/bitnami-charts_1789260948/runs/external-dns_1789261550/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Identified input fields (lower bound): 235 | Varied in render attempts: 9
Missing values: 10 | Undocumented template fields: 238
Unreferenced values: 58 (unknown)
Field variation does not prove branch or output coverage.
Phase known-inputs: failed | Attempts: 47
Phase robustness: passed | Attempts: 101
Errors: [E020](#)
Reproducing values (known-inputs):

```
{  
  "interval": "\u001f"  
}
```



bitnami/flink

Result: FAIL | Status: failed

Attempts: 188 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/flink_1789261585/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 134 | Varied in render attempts: 35

Missing values: 0 | Undocumented template fields: 139

Unreferenced values: 53 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 87

Phase robustness: passed | Attempts: 101

Errors: [E021](#)

Reproducing values (known-inputs):

```
{
  "clusterDomain": "\b"
}
```

bitnami/fluent-bit

Result: FAIL | Status: failed

Attempts: 217 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/fluent-bit_1789261621/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 121 | Varied in render attempts: 39

Missing values: 0 | Undocumented template fields: 126

Unreferenced values: 35 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 116

Phase robustness: passed | Attempts: 101

Errors: [E022](#)

Reproducing values (known-inputs):

```
{
  "nameOverride": "\u001f"
}
```

bitnami/fluentd

Result: FAIL | Status: failed

Attempts: 128 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/fluentd_1789261647/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 208 | Varied in render attempts: 16

Missing values: 7 | Undocumented template fields: 217

Unreferenced values: 64 (unknown)



Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 27

Phase robustness: passed | Attempts: 101

Errors: [E023](#)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/flux

Result: FAIL | Status: failed

Attempts: 120 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/flux_1789261654/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 543 | Varied in render attempts: 20

Missing values: 9 | Undocumented template fields: 565

Unreferenced values: 163 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 19

Phase robustness: passed | Attempts: 101

Errors: [E024](#)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/ghost

Result: FAIL | Status: failed

Attempts: 152 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/ghost_1789261679/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 121 | Varied in render attempts: 25

Missing values: 4 | Undocumented template fields: 114

Unreferenced values: 43 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 51

Phase robustness: passed | Attempts: 101

Errors: [E086](#)

Reproducing values (known-inputs):

```
{
  "mysql": {
```



```
    "architecture": ""
  }
}
```

bitnami/gitea

Result: FAIL | Status: failed
Attempts: 147 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts:
[bitnami-runs/bitnami-charts 1789260948/runs/gitea 1789261682/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Identified input fields (lower bound): 113 | Varied in render attempts: 5
Missing values: 0 | Undocumented template fields: 118
Unreferenced values: 40 (unknown)
Field variation does not prove branch or output coverage.
Phase known-inputs: failed | Attempts: 46
Phase robustness: passed | Attempts: 101
Errors: [E025](#)
Reproducing values (known-inputs):

```
{
  "smtpExistingSecret": "\u001f"
}
```

bitnami/gitlab-runner

Result: FAIL | Status: failed
Attempts: 248 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts:
[bitnami-runs/bitnami-charts 1789260948/runs/gitlab-runner 1789261710/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Identified input fields (lower bound): 142 | Varied in render attempts: 44
Missing values: 0 | Undocumented template fields: 145
Unreferenced values: 48 (unknown)
Field variation does not prove branch or output coverage.
Phase known-inputs: failed | Attempts: 147
Phase robustness: passed | Attempts: 101
Errors: [E026](#)
Reproducing values (known-inputs):

```
{
  "helperImage": {
    "digest": "\u001f"
  }
}
```



bitnami/grafana

Result: FAIL | Status: failed

Attempts: 164 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/grafana_1789261713/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 151 | Varied in render attempts: 15

Missing values: 5 | Undocumented template fields: 156

Unreferenced values: 52 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 63

Phase robustness: passed | Attempts: 101

Errors: [E031](#)

Reproducing values (known-inputs):

```
{
  "admin": {
    "existingSecret": "?"
  }
}
```

bitnami/grafana-alloy

Result: FAIL | Status: failed

Attempts: 368 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/grafana-alloy_1789261741/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 132 | Varied in render attempts: 88

Missing values: 3 | Undocumented template fields: 138

Unreferenced values: 61 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 267

Phase robustness: passed | Attempts: 101

Errors: [E093](#)

Reproducing values (known-inputs):

```
{
  "global": {
    "imageRegistry": "00"
  }
}
```

bitnami/grafana-k6-operator

Result: FAIL | Status: failed

Attempts: 173 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/grafana-k6-operator_1789261748/0000](#)

Filtering applied: True



Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 91 | Varied in render attempts: 5

Missing values: 0 | Undocumented template fields: 95

Unreferenced values: 32 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 72

Phase robustness: passed | Attempts: 101

Errors: [E027](#)

Reproducing values (known-inputs):

```
{
  "extraEnvVarsCM": "?"
}
```

bitnami/grafana-loki

Result: FAIL | Status: failed

Attempts: 148 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/grafana-loki_1789261775/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 671 | Varied in render attempts: 7

Missing values: 6 | Undocumented template fields: 696

Unreferenced values: 287 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 47

Phase robustness: passed | Attempts: 101

Errors: [E028](#)

Reproducing values (known-inputs):

```
{
  "clusterDomain": "\u001f"
}
```

bitnami/grafana-mimir

Result: FAIL | Status: failed

Attempts: 125 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/grafana-mimir_1789261802/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 703 | Varied in render attempts: 1

Missing values: 6 | Undocumented template fields: 729

Unreferenced values: 335 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 24

Phase robustness: passed | Attempts: 101

Errors: [E100](#)

Reproducing values (known-inputs):

```
{
```



```
"memcachedchunks": {
  "architecture": ""
}
}
```

bitnami/grafana-operator

Result: FAIL | Status: failed
 Attempts: 143 | Remaining iterations: unknown
 Coverage: known inputs, then original-schema robustness sampling
 Artifacts:
[bitnami-runs/bitnami-charts_1789260948/runs/grafana-operator_1789261806/0000](#)
 Filtering applied: True
 Generation order only; original-schema cases run last, not removed
 Identified input fields (lower bound): 120 | Varied in render attempts: 25
 Missing values: 1 | Undocumented template fields: 127
 Unreferenced values: 44 (unknown)
 Field variation does not prove branch or output coverage.
 Phase known-inputs: failed | Attempts: 42
 Phase robustness: passed | Attempts: 101
 Errors: [E029](#)
 Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/grafana-tempo

Result: FAIL | Status: failed
 Attempts: 138 | Remaining iterations: unknown
 Coverage: known inputs, then original-schema robustness sampling
 Artifacts:
[bitnami-runs/bitnami-charts_1789260948/runs/grafana-tempo_1789261832/0000](#)
 Filtering applied: True
 Generation order only; original-schema cases run last, not removed
 Identified input fields (lower bound): 469 | Varied in render attempts: 3
 Missing values: 2 | Undocumented template fields: 489
 Unreferenced values: 204 (unknown)
 Field variation does not prove branch or output coverage.
 Phase known-inputs: failed | Attempts: 37
 Phase robustness: passed | Attempts: 101
 Errors: [E030](#)
 Reproducing values (known-inputs):

```
{
  "tempo": {
    "configuration": "\u001f"
  }
}
```



bitnami/haproxy

Result: FAIL | Status: failed

Attempts: 192 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/haproxy_1789261927/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 87 | Varied in render attempts: 56

Missing values: 0 | Undocumented template fields: 91

Unreferenced values: 34 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 91

Phase robustness: passed | Attempts: 101

Errors: [E032](#)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/harbor

Result: FAIL | Status: failed

Attempts: 137 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/harbor_1789261928/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 554 | Varied in render attempts: 2

Missing values: 4 | Undocumented template fields: 586

Unreferenced values: 294 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 36

Phase robustness: passed | Attempts: 101

Errors: [E033](#)

Reproducing values (known-inputs):

```
{
  "existingSecret": "\u001f"
}
```

bitnami/influxdb

Result: FAIL | Status: failed

Attempts: 380 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/influxdb_1789261931/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 167 | Varied in render attempts: 119



Missing values: 0 | Undocumented template fields: 174
Unreferenced values: 51 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 279

Phase robustness: passed | Attempts: 101

Errors: [E094](#)

Reproducing values (known-inputs):

```
{
  "global": {
    "imageRegistry": "00"
  }
}
```

bitnami/jaeger

Result: FAIL | Status: failed

Attempts: 220 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/jaeger_1789261953/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 155 | Varied in render attempts: 7

Missing values: 0 | Undocumented template fields: 160

Unreferenced values: 101 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 119

Phase robustness: passed | Attempts: 101

Errors: [E034](#)

Reproducing values (known-inputs):

```
{
  "fullnameOverride": ""
}
```

bitnami/janusgraph

Result: FAIL | Status: failed

Attempts: 139 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/janusgraph_1789261985/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 125 | Varied in render attempts: 2

Missing values: 6 | Undocumented template fields: 134

Unreferenced values: 52 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 38

Phase robustness: passed | Attempts: 101

Errors: [E035](#)

Reproducing values (known-inputs):

```
{
  "existingConfigmap": "\u001f"
```



```
}
```

bitnami/jenkins

Result: FAIL | Status: failed

Attempts: 426 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/jenkins_1789261998/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 172 | Varied in render attempts: 15

Missing values: 0 | Undocumented template fields: 171

Unreferenced values: 43 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 118

Phase robustness: failed | Attempts: 308

Errors: [E112](#), [E036](#)

Reproducing values (known-inputs):

```
{
  "fullnameOverride": "0"
}
```

Reproducing values (robustness):

```
{
  "": [],
  "service": {
    "type": ":"
  }
}
```

bitnami/jupyterhub

Result: FAIL | Status: failed

Attempts: 125 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/jupyterhub_1789262019/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 252 | Varied in render attempts: 1

Missing values: 4 | Undocumented template fields: 262

Unreferenced values: 102 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 24

Phase robustness: passed | Attempts: 101

Errors: [E095](#)

Reproducing values (known-inputs):

```
{
  "singleuser": {
    "resourcesPreset": ""
  }
}
```



bitnami/kafka

Result: FAIL | Status: failed

Attempts: 141 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/kafka_1789262019/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 356 | Varied in render attempts: 2

Missing values: 3 | Undocumented template fields: 372

Unreferenced values: 154 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 40

Phase robustness: passed | Attempts: 101

Errors: [E037](#)

Reproducing values (known-inputs):

```
{
  "dnsPolicy": "\u001f"
}
```

bitnami/keycloak

Result: FAIL | Status: failed

Attempts: 214 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/keycloak_1789262075/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 232 | Varied in render attempts: 93

Missing values: 0 | Undocumented template fields: 239

Unreferenced values: 64 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 113

Phase robustness: passed | Attempts: 101

Errors: [E111](#)

Reproducing values (known-inputs):

```
{
  "dnsPolicy": "\u001f"
}
```

bitnami/keydb

Result: FAIL | Status: failed

Attempts: 127 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/keydb_1789262081/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 207 | Varied in render attempts: 4

Missing values: 3 | Undocumented template fields: 218

Unreferenced values: 119 (unknown)



Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 26

Phase robustness: passed | Attempts: 101

Errors: [E112](#)

Reproducing values (known-inputs):

```
{
  "fullnameOverride": "0"
}
```

bitnami/kibana

Result: FAIL | Status: failed

Attempts: 254 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/kibana_1789262084/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 139 | Varied in render attempts: 42

Missing values: 1 | Undocumented template fields: 144

Unreferenced values: 30 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 153

Phase robustness: passed | Attempts: 101

Errors: [E038](#)

Reproducing values (known-inputs):

```
{
  "ingress": {
    "enabled": true,
    "hostname": "\u001f"
  }
}
```

bitnami/kong

Result: FAIL | Status: failed

Attempts: 140 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/kong_1789262120/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 156 | Varied in render attempts: 1

Missing values: 9 | Undocumented template fields: 160

Unreferenced values: 84 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 39

Phase robustness: passed | Attempts: 101

Errors: [E039](#)

Reproducing values (known-inputs):

```
{
  "terminationGracePeriodSeconds": "-"
}
```



bitnami/kube-arangodb

Result: FAIL | Status: failed

Attempts: 163 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/kube-arangodb_1789262121/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 153 | Varied in render attempts: 4

Missing values: 0 | Undocumented template fields: 158

Unreferenced values: 61 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 62

Phase robustness: passed | Attempts: 101

Errors: [E040](#)

Reproducing values (known-inputs):

```
{
  "nameOverride": "\u001f"
}
```

bitnami/kube-prometheus

Result: FAIL | Status: failed

Attempts: 120 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/kube-prometheus_1789262132/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 691 | Varied in render attempts: 18

Missing values: 6 | Undocumented template fields: 711

Unreferenced values: 83 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 19

Phase robustness: passed | Attempts: 101

Errors: [E110](#)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/kube-prometheus/charts/kube-prometheus-crds

Result: FAIL | Status: failed

Attempts: 2 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/kube-prometheus-crds_1789262163/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 0 | Varied in render attempts: 0



Missing values: 0 | Undocumented template fields: 0
Unreferenced values: 1 (possibly unused; not proven)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 1

Phase robustness: failed | Attempts: 1

Errors: [E087](#)

Reproducing values (known-inputs):

```
{}
```

Reproducing values (robustness):

```
{}
```

bitnami/kube-state-metrics

Result: FAIL | Status: failed

Attempts: 118 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/kube-state-metrics_1789262164/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 117 | Varied in render attempts: 2

Missing values: 1 | Undocumented template fields: 120

Unreferenced values: 32 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 17

Phase robustness: passed | Attempts: 101

Errors: [E096](#)

Reproducing values (known-inputs):

```
{
  "resourcesPreset": ""
}
```

bitnami/kuberay

Result: FAIL | Status: failed

Attempts: 134 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/kuberay_1789262165/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 283 | Varied in render attempts: 2

Missing values: 0 | Undocumented template fields: 295

Unreferenced values: 64 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 33

Phase robustness: passed | Attempts: 101

Errors: [E041](#)

Reproducing values (known-inputs):

```
{
  "commonAnnotations": {
    "": []
  }
}
```



```
}  
}
```

bitnami/kubernetes-event-exporter

Result: FAIL | Status: failed
Attempts: 191 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts:
[bitnami-runs/bitnami-charts_1789260948/runs/kubernetes-event-exporter_1789262168/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Identified input fields (lower bound): 82 | Varied in render attempts: 23
Missing values: 2 | Undocumented template fields: 87
Unreferenced values: 33 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 90
Phase robustness: passed | Attempts: 101

Errors: [E042](#)

Reproducing values (known-inputs):

```
{  
  "commonAnnotations": {  
    "": null  
  }  
}
```

bitnami/logstash

Result: FAIL | Status: failed
Attempts: 141 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts:
[bitnami-runs/bitnami-charts_1789260948/runs/logstash_1789262184/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Identified input fields (lower bound): 110 | Varied in render attempts: 4
Missing values: 5 | Undocumented template fields: 119
Unreferenced values: 27 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 40
Phase robustness: passed | Attempts: 101

Errors: [E043](#)

Reproducing values (known-inputs):

```
{  
  "existingConfiguration": "\u001f"  
}
```

bitnami/mariadb

Result: FAIL | Status: failed
Attempts: 132 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts:
[bitnami-runs/bitnami-charts_1789260948/runs/mariadb_1789262195/0000](#)

Filtering applied: True



Generation order only; original-schema cases run last, not removed
Identified input fields (lower bound): 242 | Varied in render attempts: 72
Missing values: 12 | Undocumented template fields: 22
Unreferenced values: 81 (unknown)
Field variation does not prove branch or output coverage.
Phase known-inputs: failed | Attempts: 5
Phase robustness: failed | Attempts: 127
Errors: [E099](#)
Reproducing values (known-inputs):

```
{  
  "architecture": ""  
}
```

Reproducing values (robustness):

```
{  
  "": [],  
  "architecture": ""  
}
```

bitnami/mariadb-galera

Result: FAIL | Status: failed
Attempts: 128 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts:
[bitnami-runs/bitnami-charts_1789260948/runs/mariadb-galera_1789262206/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Identified input fields (lower bound): 139 | Varied in render attempts: 38
Missing values: 10 | Undocumented template fields: 127
Unreferenced values: 50 (unknown)
Field variation does not prove branch or output coverage.
Phase known-inputs: failed | Attempts: 100
Phase robustness: time-limit | Attempts: 28
Errors: [E097](#)
Reproducing values (known-inputs):

```
{  
  "resourcesPreset": ""  
}
```

bitnami/mastodon

Result: FAIL | Status: failed
Attempts: 160 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts:
[bitnami-runs/bitnami-charts_1789260948/runs/mastodon_1789262219/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Identified input fields (lower bound): 284 | Varied in render attempts: 16
Missing values: 5 | Undocumented template fields: 300
Unreferenced values: 150 (unknown)
Field variation does not prove branch or output coverage.
Phase known-inputs: failed | Attempts: 59



Phase robustness: passed | Attempts: 101

Errors: [E112](#)

Reproducing values (known-inputs):

```
{
  "serviceAccount": {
    "name": ""
  }
}
```

bitnami/matomo

Result: FAIL | Status: failed

Attempts: 134 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/matomo_1789262257/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 160 | Varied in render attempts: 3

Missing values: 0 | Undocumented template fields: 170

Unreferenced values: 53 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 33

Phase robustness: passed | Attempts: 101

Errors: [E044](#)

Reproducing values (known-inputs):

```
{
  "extraEnvVarsCM": "\u001f"
}
```

bitnami/memcached

Result: FAIL | Status: failed

Attempts: 146 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/memcached_1789262312/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 122 | Varied in render attempts: 27

Missing values: 1 | Undocumented template fields: 129

Unreferenced values: 46 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 45

Phase robustness: passed | Attempts: 101

Errors: [E101](#)

Reproducing values (known-inputs):

```
{
  "architecture": ""
}
```



bitnami/metallb

Result: FAIL | Status: failed

Attempts: 160 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/metallb_1789262350/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 166 | Varied in render attempts: 7

Missing values: 3 | Undocumented template fields: 174

Unreferenced values: 75 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 59

Phase robustness: passed | Attempts: 101

Errors: [E045](#)

Reproducing values (known-inputs):

```
{
  "commonAnnotations": {
    "": []
  }
}
```

bitnami/metrics-server

Result: FAIL | Status: failed

Attempts: 199 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/metrics-server_1789262363/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 72 | Varied in render attempts: 13

Missing values: 0 | Undocumented template fields: 75

Unreferenced values: 32 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 98

Phase robustness: passed | Attempts: 101

Errors: [E046](#)

Reproducing values (known-inputs):

```
{
  "dnsPolicy": "\u001f"
}
```

bitnami/milvus

Result: N/A | Status: time-limit

Attempts: 30 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/milvus_1789262386/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 601 | Varied in render attempts: 3



Missing values: 1 | Undocumented template fields: 32
Unreferenced values: 227 (unknown)
Field variation does not prove branch or output coverage.
Phase known-inputs: time-limit | Attempts: 23
Phase robustness: time-limit | Attempts: 7

bitnami/mlflow

Result: FAIL | Status: failed
Attempts: 251 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts:
[bitnami-runs/bitnami-charts 1789260948/runs/mlflow 1789262402/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Identified input fields (lower bound): 217 | Varied in render attempts: 20
Missing values: 3 | Undocumented template fields: 18
Unreferenced values: 110 (unknown)
Field variation does not prove branch or output coverage.
Phase known-inputs: failed | Attempts: 120
Phase robustness: failed | Attempts: 131
Errors: [E083](#), [E047](#)

Reproducing values (known-inputs):

```
{
  "volumePermissions": {
    "enabled": true
  }
}
```

Reproducing values (robustness):

```
{
  "nameOverride": "\u001f",
  "": []
}
```

bitnami/mongodb

Result: FAIL | Status: failed
Attempts: 101 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts:
[bitnami-runs/bitnami-charts 1789260948/runs/mongodb 1789262443/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Identified input fields (lower bound): 348 | Varied in render attempts: 7
Missing values: 5 | Undocumented template fields: 348
Unreferenced values: 141 (unknown)
Field variation does not prove branch or output coverage.
Phase known-inputs: failed | Attempts: 43
Phase robustness: time-limit | Attempts: 58
Errors: [E049](#)

Reproducing values (known-inputs):

```
{
  "configuration": "\u001f"
```



}

bitnami/mongodb-sharded

Result: FAIL | Status: failed

Attempts: 145 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/mongodb-sharded_1789262509/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 280 | Varied in render attempts: 2

Missing values: 2 | Undocumented template fields: 306

Unreferenced values: 7 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 44

Phase robustness: passed | Attempts: 101

Errors: [E048](#)

Reproducing values (known-inputs):

```
{
  "clusterDomain": "\u001f"
}
```

bitnami/moodle

Result: FAIL | Status: failed

Attempts: 242 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/moodle_1789262603/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 140 | Varied in render attempts: 45

Missing values: 3 | Undocumented template fields: 147

Unreferenced values: 51 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 141

Phase robustness: passed | Attempts: 101

Errors: [E050](#)

Reproducing values (known-inputs):

```
{
  "extraEnvVarsCM": "\u001f"
}
```

bitnami/multus-cni

Result: FAIL | Status: failed

Attempts: 135 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/multus-cni_1789262612/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 51 | Varied in render attempts: 2

Missing values: 1 | Undocumented template fields: 54



Unreferenced values: 36 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 34

Phase robustness: passed | Attempts: 101

Errors: [E051](#)

Reproducing values (known-inputs):

```
{
  "CNIMountPath": ">"
}
```

bitnami/mysql

Result: FAIL | Status: failed

Attempts: 239 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/mysql_1789262639/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 235 | Varied in render attempts: 40

Missing values: 6 | Undocumented template fields: 226

Unreferenced values: 86 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 138

Phase robustness: passed | Attempts: 101

Errors: [E052](#)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/nats

Result: FAIL | Status: failed

Attempts: 327 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/nats_1789262668/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 129 | Varied in render attempts: 51

Missing values: 0 | Undocumented template fields: 135

Unreferenced values: 70 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 226

Phase robustness: passed | Attempts: 101

Errors: [E053](#)

Reproducing values (known-inputs):

```
{
  "nameOverride": "\u001f"
}
```



bitnami/neo4j

Result: FAIL | Status: failed

Attempts: 137 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/neo4j_1789262693/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 123 | Varied in render attempts: 9

Missing values: 0 | Undocumented template fields: 131

Unreferenced values: 32 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 36

Phase robustness: passed | Attempts: 101

Errors: [E112](#)

Reproducing values (known-inputs):

```
{
  "fullnameOverride": ""
}
```

bitnami/nessie

Result: FAIL | Status: failed

Attempts: 184 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/nessie_1789262730/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 141 | Varied in render attempts: 29

Missing values: 1 | Undocumented template fields: 147

Unreferenced values: 59 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 83

Phase robustness: passed | Attempts: 101

Errors: [E054](#)

Reproducing values (known-inputs):

```
{
  "annotations": {
    "": []
  }
}
```

bitnami/nginx

Result: FAIL | Status: failed

Attempts: 325 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/nginx_1789262745/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 170 | Varied in render attempts: 108



Missing values: 2 | Undocumented template fields: 159
Unreferenced values: 58 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 84

Phase robustness: failed | Attempts: 241

Errors: [E056](#), [E055](#)

Reproducing values (known-inputs):

```
{
  "existingContextEventsConfigmaps": [
    "\u001f"
  ]
}
```

Reproducing values (robustness):

```
{
  "contextIncludes": {
    "events": "\u001f",
    "": []
  }
}
```

bitnami/node-exporter

Result: FAIL | Status: failed

Attempts: 240 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/node-exporter_1789262746/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 85 | Varied in render attempts: 23

Missing values: 1 | Undocumented template fields: 88

Unreferenced values: 35 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 139

Phase robustness: passed | Attempts: 101

Errors: [E114](#)

Reproducing values (known-inputs):

```
{
  "kubeVersion": ":"
}
```

bitnami/oauth2-proxy

Result: FAIL | Status: failed

Attempts: 130 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/oauth2-proxy_1789262793/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 103 | Varied in render attempts: 23

Missing values: 0 | Undocumented template fields: 106

Unreferenced values: 50 (unknown)

Field variation does not prove branch or output coverage.



Phase known-inputs: failed | Attempts: 29

Phase robustness: passed | Attempts: 101

Errors: [E105](#)

Reproducing values (known-inputs):

```
{
  "redis": {
    "architecture": ""
  }
}
```

bitnami/odoo

Result: FAIL | Status: failed

Attempts: 128 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts 1789260948/runs/odoo 1789262798/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 122 | Varied in render attempts: 12

Missing values: 4 | Undocumented template fields: 127

Unreferenced values: 42 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 27

Phase robustness: passed | Attempts: 101

Errors: [E102](#)

Reproducing values (known-inputs):

```
{
  "resourcesPreset": ""
}
```

bitnami/opensearch

Result: FAIL | Status: failed

Attempts: 206 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts 1789260948/runs/opensearch 1789262840/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 523 | Varied in render attempts: 17

Missing values: 17 | Undocumented template fields: 546

Unreferenced values: 217 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 105

Phase robustness: passed | Attempts: 101

Errors: [E057](#)

Reproducing values (known-inputs):

```
{
  "extraEnvVarsCM": ":"
}
```



bitnami/parse

Result: FAIL | Status: failed

Attempts: 120 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/parse_1789262841/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 165 | Varied in render attempts: 21

Missing values: 0 | Undocumented template fields: 173

Unreferenced values: 61 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 19

Phase robustness: passed | Attempts: 101

Errors: [E058](#)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/phpmyadmin

Result: FAIL | Status: failed

Attempts: 234 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/phpmyadmin_1789262890/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 120 | Varied in render attempts: 27

Missing values: 5 | Undocumented template fields: 124

Unreferenced values: 36 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 133

Phase robustness: passed | Attempts: 101

Errors: [E112](#)

Reproducing values (known-inputs):

```
{
  "serviceAccount": {
    "name": ""
  }
}
```

bitnami/pinniped

Result: FAIL | Status: failed

Attempts: 160 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/pinniped_1789262910/0000](#)

Filtering applied: True



Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 173 | Varied in render attempts: 1

Missing values: 0 | Undocumented template fields: 180

Unreferenced values: 56 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 59

Phase robustness: passed | Attempts: 101

Errors: [E059](#)

Reproducing values (known-inputs):

```
{
  "fullnameOverride": ""
}
```

bitnami/postgresql

Result: FAIL | Status: failed

Attempts: 280 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/postgresql_1789262926/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 310 | Varied in render attempts: 21

Missing values: 7 | Undocumented template fields: 314

Unreferenced values: 106 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 15

Phase robustness: failed | Attempts: 265

Errors: [E103](#), [E061](#)

Reproducing values (known-inputs):

```
{
  "psp": {
    "create": true
  }
}
```

Reproducing values (robustness):

```
{
  "": [],
  "auth": {
    "database": "\u001f"
  }
}
```

bitnami/postgresql-ha

Result: FAIL | Status: failed

Attempts: 157 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/postgresql-ha_1789262929/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 371 | Varied in render attempts: 18



Missing values: 3 | Undocumented template fields: 386
Unreferenced values: 121 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 56

Phase robustness: passed | Attempts: 101

Errors: [E060](#)

Reproducing values (known-inputs):

```
{
  "clusterDomain": "\u001f"
}
```

bitnami/prometheus

Result: FAIL | Status: failed

Attempts: 345 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts 1789260948/runs/prometheus 1789262960/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 230 | Varied in render attempts: 18

Missing values: 0 | Undocumented template fields: 10

Unreferenced values: 86 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 93

Phase robustness: failed | Attempts: 252

Errors: [E062](#), [E063](#)

Reproducing values (known-inputs):

```
{
  "nameOverride": "\u001f"
}
```

Reproducing values (robustness):

```
{
  "": [],
  "extraDeploy": [
    []
  ]
}
```

bitnami/pytorch

Result: FAIL | Status: failed

Attempts: 179 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts 1789260948/runs/pytorch 1789262979/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 87 | Varied in render attempts: 17

Missing values: 8 | Undocumented template fields: 92

Unreferenced values: 38 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 78



Phase robustness: passed | Attempts: 101

Errors: [E104](#)

Reproducing values (known-inputs):

```
{
  "architecture": ""
}
```

bitnami/rabbitmq

Result: FAIL | Status: failed

Attempts: 185 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts 1789260948/runs/rabbitmq 1789262993/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 215 | Varied in render attempts: 28

Missing values: 1 | Undocumented template fields: 213

Unreferenced values: 94 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 84

Phase robustness: passed | Attempts: 101

Errors: [E065](#)

Reproducing values (known-inputs):

```
{
  "hostPorts": {
    "amqp": "\u001f"
  }
}
```

bitnami/rabbitmq-cluster-operator

Result: FAIL | Status: failed

Attempts: 230 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts 1789260948/runs/rabbitmq-cluster-operator 1789263004/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 206 | Varied in render attempts: 90

Missing values: 3 | Undocumented template fields: 212

Unreferenced values: 53 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 129

Phase robustness: passed | Attempts: 101

Errors: [E064](#)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```



bitnami/redis

Result: FAIL | Status: failed

Attempts: 134 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts 1789260948/runs/redis 1789263022/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 350 | Varied in render attempts: 67

Missing values: 6 | Undocumented template fields: 29

Unreferenced values: 133 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 5

Phase robustness: failed | Attempts: 129

Errors: [E106](#)

Reproducing values (known-inputs):

```
{
  "architecture": ""
}
```

Reproducing values (robustness):

```
{
  "": [],
  "architecture": ""
}
```

bitnami/redis-cluster

Result: FAIL | Status: failed

Attempts: 148 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts 1789260948/runs/redis-cluster 1789263038/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 175 | Varied in render attempts: 4

Missing values: 1 | Undocumented template fields: 184

Unreferenced values: 51 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 47

Phase robustness: passed | Attempts: 101

Errors: [E066](#)

Reproducing values (known-inputs):

```
{
  "existingSecret": "-"
}
```



bitnami/redmine

Result: FAIL | Status: failed

Attempts: 516 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts 1789260948/runs/redmine 1789263074/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 157 | Varied in render attempts: 50

Missing values: 9 | Undocumented template fields: 153

Unreferenced values: 66 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 104

Phase robustness: failed | Attempts: 412

Errors: [E067](#), [E068](#)

Reproducing values (known-inputs):

```
{
  "terminationGracePeriodSeconds": "\u001f"
}
```

Reproducing values (robustness):

```
{
  "": [],
  "service": {
    "type": "-"
  }
}
```

bitnami/schema-registry

Result: FAIL | Status: failed

Attempts: 171 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts 1789260948/runs/schema-registry 1789263074/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 119 | Varied in render attempts: 35

Missing values: 5 | Undocumented template fields: 122

Unreferenced values: 35 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 70

Phase robustness: passed | Attempts: 101

Errors: [E084](#)

Reproducing values (known-inputs):

```
{
  "httpRoutes": [
    null
  ]
}
```



bitnami/scylladb

Result: FAIL | Status: failed

Attempts: 209 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/scylladb_1789263109/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 161 | Varied in render attempts: 79

Missing values: 0 | Undocumented template fields: 169

Unreferenced values: 82 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 108

Phase robustness: passed | Attempts: 101

Errors: [E085](#)

Reproducing values (known-inputs):

```
{
  "extraContainerPorts": [
    null
  ]
}
```

bitnami/sealed-secrets

Result: FAIL | Status: failed

Attempts: 164 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/sealed-secrets_1789263115/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 114 | Varied in render attempts: 4

Missing values: 0 | Undocumented template fields: 117

Unreferenced values: 33 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 63

Phase robustness: passed | Attempts: 101

Errors: [E107](#)

Reproducing values (known-inputs):

```
{
  "resourcesPreset": ""
}
```

bitnami/seaweedfs

Result: FAIL | Status: failed

Attempts: 135 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/seaweedfs_1789263116/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 578 | Varied in render attempts: 3



Missing values: 6 | Undocumented template fields: 610
Unreferenced values: 250 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 34

Phase robustness: passed | Attempts: 101

Errors: [E069](#)

Reproducing values (known-inputs):

```
{
  "clusterDomain": "\u001f"
}
```

bitnami/solr

Result: FAIL | Status: failed

Attempts: 213 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/solr_1789263147/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 168 | Varied in render attempts: 71

Missing values: 1 | Undocumented template fields: 176

Unreferenced values: 66 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 112

Phase robustness: passed | Attempts: 101

Errors: [E070](#)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/sonarqube

Result: FAIL | Status: failed

Attempts: 129 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/sonarqube_1789263200/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 165 | Varied in render attempts: 8

Missing values: 0 | Undocumented template fields: 181

Unreferenced values: 55 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 28

Phase robustness: passed | Attempts: 101

Errors: [E071](#)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
```



```
[ ]
]
```

bitnami/spark

Result: FAIL | Status: failed
 Attempts: 129 | Remaining iterations: unknown
 Coverage: known inputs, then original-schema robustness sampling
 Artifacts:
[bitnami-runs/bitnami-charts_1789260948/runs/spark_1789263236/0000](#)
 Filtering applied: True
 Generation order only; original-schema cases run last, not removed
 Identified input fields (lower bound): 180 | Varied in render attempts: 1
 Missing values: 0 | Undocumented template fields: 185
 Unreferenced values: 57 (unknown)
 Field variation does not prove branch or output coverage.
 Phase known-inputs: failed | Attempts: 28
 Phase robustness: passed | Attempts: 101
 Errors: [E112](#)
 Reproducing values (known-inputs):
 {
 "fullnameOverride": "0"
 }

bitnami/superset

Result: FAIL | Status: failed
 Attempts: 137 | Remaining iterations: unknown
 Coverage: known inputs, then original-schema robustness sampling
 Artifacts:
[bitnami-runs/bitnami-charts_1789260948/runs/superset_1789263238/0000](#)
 Filtering applied: True
 Generation order only; original-schema cases run last, not removed
 Identified input fields (lower bound): 299 | Varied in render attempts: 6
 Missing values: 1 | Undocumented template fields: 313
 Unreferenced values: 161 (unknown)
 Field variation does not prove branch or output coverage.
 Phase known-inputs: failed | Attempts: 36
 Phase robustness: passed | Attempts: 101
 Errors: [E072](#)
 Reproducing values (known-inputs):
 {
 "extraDeploy": [
 [
]
]
}



bitnami/tensorflow-resnet

Result: FAIL | Status: failed

Attempts: 215 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/tensorflow-resnet_1789263255/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 73 | Varied in render attempts: 30

Missing values: 4 | Undocumented template fields: 77

Unreferenced values: 30 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 114

Phase robustness: passed | Attempts: 101

Errors: [E073](#)

Reproducing values (known-inputs):

```
{
  "service": {
    "loadBalancerIP": ":"
  }
}
```

bitnami/thanos

Result: FAIL | Status: failed

Attempts: 155 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/thanos_1789263263/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 971 | Varied in render attempts: 36

Missing values: 62 | Undocumented template fields: 992

Unreferenced values: 242 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 54

Phase robustness: passed | Attempts: 101

Errors: [E074](#)

Reproducing values (known-inputs):

```
{
  "bucketCacheConfig": "\u001f"
}
```

bitnami/tomcat

Result: FAIL | Status: failed

Attempts: 144 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/tomcat_1789263266/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 80 | Varied in render attempts: 0



Missing values: 5 | Undocumented template fields: 82
Unreferenced values: 93 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 43

Phase robustness: passed | Attempts: 101

Errors: [E075](#)

Reproducing values (known-inputs):

```
{
  "extraEnvVarsCM": "\u001f"
}
```

bitnami/valkey

Result: FAIL | Status: failed

Attempts: 140 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/valkey_1789263282/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 311 | Varied in render attempts: 13

Missing values: 1 | Undocumented template fields: 314

Unreferenced values: 132 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 39

Phase robustness: passed | Attempts: 101

Errors: [E077](#)

Reproducing values (known-inputs):

```
{
  "clusterDomain": "\u001f"
}
```

bitnami/valkey-cluster

Result: FAIL | Status: failed

Attempts: 134 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/valkey-cluster_1789263288/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 168 | Varied in render attempts: 51

Missing values: 0 | Undocumented template fields: 177

Unreferenced values: 49 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 33

Phase robustness: passed | Attempts: 101

Errors: [E076](#)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```



```
}
```

bitnami/vault

Result: FAIL | Status: failed

Attempts: 168 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/vault_1789263307/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 259 | Varied in render attempts: 7

Missing values: 1 | Undocumented template fields: 273

Unreferenced values: 94 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 67

Phase robustness: passed | Attempts: 101

Errors: [E078](#)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/victoriametrics

Result: FAIL | Status: failed

Attempts: 174 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/victoriametrics_1789263322/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 591 | Varied in render attempts: 4

Missing values: 0 | Undocumented template fields: 617

Unreferenced values: 129 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 73

Phase robustness: passed | Attempts: 101

Errors: [E079](#)

Reproducing values (known-inputs):

```
{
  "loggerFormat": "\u001f"
}
```

bitnami/whereabouts

Result: FAIL | Status: failed

Attempts: 120 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/whereabouts_1789263358/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed



Identified input fields (lower bound): 48 | Varied in render attempts: 4
Missing values: 0 | Undocumented template fields: 51
Unreferenced values: 33 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 19

Phase robustness: passed | Attempts: 101

Errors: [E108](#)

Reproducing values (known-inputs):

```
{
  "resourcesPreset": ""
}
```

bitnami/wildfly

Result: FAIL | Status: failed

Attempts: 145 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/wildfly_1789263365/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 110 | Varied in render attempts: 2

Missing values: 6 | Undocumented template fields: 116

Unreferenced values: 36 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 44

Phase robustness: passed | Attempts: 101

Errors: [E112](#)

Reproducing values (known-inputs):

```
{
  "fullnameOverride": ""
}
```

bitnami/wordpress

Result: FAIL | Status: failed

Attempts: 395 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts_1789260948/runs/wordpress_1789263373/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 177 | Varied in render attempts: 41

Missing values: 5 | Undocumented template fields: 170

Unreferenced values: 84 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 122

Phase robustness: failed | Attempts: 273

Errors: [E080](#), [E081](#)

Reproducing values (known-inputs):

```
{
  "apacheConfiguration": "\u001f"
}
```



Reproducing values (robustness):

```
{
  "": [],
  "service": {
    "type": "?"
  }
}
```

bitnami/zipkin

Result: FAIL | Status: failed

Attempts: 2 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts 1789260948/runs/zipkin 1789263388/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 135 | Varied in render attempts: 0

Missing values: 1 | Undocumented template fields: 140

Unreferenced values: 77 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 1

Phase robustness: failed | Attempts: 1

Errors: [E109](#)

Reproducing values (known-inputs):

```
{}
```

Reproducing values (robustness):

```
{}
```

bitnami/zookeeper

Result: FAIL | Status: failed

Attempts: 131 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts:

[bitnami-runs/bitnami-charts 1789260948/runs/zookeeper 1789263392/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 166 | Varied in render attempts: 1

Missing values: 2 | Undocumented template fields: 173

Unreferenced values: 46 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 30

Phase robustness: passed | Attempts: 101

Errors: [E082](#)

Reproducing values (known-inputs):

```
{
  "dataLogDir": "-"
}
```