Audio Experiment 10 - Lab Notes

Lab 8 | 6/10/2026 | Transcribed from the two handwritten pages

Steps

1. Connect power and adapter.
2. USB to system.
3. Microphone to kit (MIC port).
4. Switch off speaker first.
5. Open Code Composer Studio.
6. New CCS project:
    - Target: 6748 LCDK
    - Version: XDS100V3 connection
    - Project name
    - Compiler version: 7.4.18
    - In desktop → DSP → Realtime → supporting file → linker dsp
    - Minimize CC Studio.
7. Open DSP file → Realtime → Audio → echo.
8. Add supporting file (Project Explorer):
    - Right-click on name.
    - Add files.
    - Go to desktop → DSP → Realtime → supporting files.
    - Add everything except linker (4 files).
    - Open & copy files.
9. Right-click on project name.
10. Show build settings → include options → small green file button → Browse → Desktop → DSP → Realtime → supporting files → BSL → INC → select full folder.
11. Apply & Close.
12. Build (hammer).
13. Debug (green code load).
14. Play.

Additional notes

- In lab exam, codes won’t be given.
- 3rd November.
- Workspace – V12 → top left one to work.

Some crossed-out words on page 1 were replaced by adjacent handwritten words. The red mark on page 2 appears to be initials or a signature.