

**LISTA GREŠAKA SA FISKALNOG UREĐAJA (NA DISPLEJU FU)**

<b>NAZIV GREŠKE</b>	<b>Kod greške</b>
EC_FR_DISK_ERR	10001
EC_FR_INT_ERR	10002
EC_FR_NOT_READY	10003
EC_FR_NO_FILE	4
EC_FR_NO_PATH	5
EC_FR_INVALID_NAME	6
EC_FR_DENIED	10007
EC_FR_EXIST	10008
EC_FR_INVALID_OBJECT	10009
EC_FR_WRITE_PROTECTED	10010
EC_FR_INVALID_DRIVE	10011
EC_FR_NOT_ENABLED	10012
EC_FR_NO_FILESYSTEM	10013
EC_FR_MKFS_ABORTED	10014
EC_FR_TIMEOUT	10015
EC_FR_LOCKED	10016
EC_FR_NOT_ENOUGH_CORE	10017
EC_FR_TOO_MANY_OPEN_FILES	10018
EC_FR_INVALID_PARAMETER	10019
ERROR_EJ_NO_FILE	20
ERROR_FISCAL_FORBIDEN_PERIOD	100
ERROR_FISCAL_SERVICE_MODE	101
ERROR_FISCAL_ITEM_NOT_PROGRAMMED	102
ERROR_FISCAL_NOT_CONFIRMED	103
ERROR_FISCAL_SAME_Z_REPORT_DATETIME	104
ERROR_FISCAL_OPERATION_CANCELED	105
ERROR_FISCAL_OPERATION_NOT_ALLOWED	106
ERROR_FISCAL_CANNOT_DELETE_CASHIER_1	107
ERROR_FISCAL_INSUFFICIENT_MONEY	108
ERROR_FISCAL_INVALID_TAX_VALUE	109
ERROR_FISCAL_INVALID_TAX_CHANGE_NUMBER	110
ERROR_FISCAL_INVALID_STATUS	

ERROR_FISCAL_INVALID_LAST_FISCAL_DATE	112
ERROR_FISCAL_INVALID_INVOICE_FILE	113
ERROR_FISCAL_INVALID_FISCALIZATION_DATA	114
ERROR_FISCAL_INVALID_FACTORY_DATA	115
ERROR_FISCAL_INVALID_DATETIME	116
ERROR_FISCAL_INVALID_INPUT	117
ERROR_FISCAL_INVALID_PERIOD	118
ERROR_FISCAL_PASSWORD_INVALID_FOR_USER	119
ERROR_FISCAL_SAME_TAXES	120
ERROR_FISCAL_DEVICE_NOT_FISCALIZED	121
ERROR_FISCAL_NO_DATA_FOR_TRANSFER	122
ERROR_FISCAL_TAX_UNDEFINED	123
ERROR_FISCAL_TAX_CALC_OVERFLOW	124
ERROR_FISCAL_INVALID_ITEM_NAME	125
ERROR_FISCAL_INVALID_ITEM_PLU	126
ERROR_FISCAL_INVALID_ITEM_TAX	127
ERROR_FISCAL_INVALID_ITEM_PRICE	128
ERROR_FISCAL_NO_JUMPER	129
ERROR_FISCAL_INVALID_COUNTERS	10130
ERROR_FISCAL_DECRYPT_FAILED	131
ERROR_FISCAL_TEST_MODE	132
ERROR_FISCAL_INVALID_SUBTOTAL	133
ERROR_TRANSFER_TT_FILE	137
ERROR_FISCAL_BACKUP_HEADER_FAILED	10134
ERROR_FISCAL_BT_WRONG_PIN	135
ERROR_FISCAL_RAM_EEPROM_COUNTER_MISMATCH	136
ERROR_TRANSFER_INVALID_CMD	200
ERROR_INT_OVERFLOW	202
ERROR_MISMATCH	203
GLOBAL_ERROR	204
INVALID_ARGUMENT	205
RTC_RANGE_ERROR	206
ERROR_FM_READ_CHECKSUM_INVALID	10207
ERROR_FM_READ_NO_DATA	208
SPI_ERROR	300
SPI_WRITE_FAILED	301
SPI_NO_DATA	302
SDCARD_FILESYSTEM_NOT_READY	350
SDCARD_FILE_NOT_FOUND	351
SDCARD_INVALID_FILE_PATH	352
SDCARD_INVALID_FILE_NAME	353
UART_NO_DATA	400
UART_MODEM_WRITE_FAILED	401
UART_INVALID_UART_REGISTER	402

UART_DMA_ERROR	403
MODEM_IS_ON	500
MODEM_IS_OFF	501
MODEM_BAUDRATE_INIT_FAILED	502
MODEM_SIM_PIN_REQUIRED	503
MODEM_SIM_PIN_STATUS_ERROR	504
MODEM_NO_SIM_CARD	505
MODEM_SIM_PUK_REQUIRED	506
MODEM_PIN_ENABLED	507
MODEM_PIN_WRONG	508
MODEM_GPRS_ERROR	509
MODEM_GPRS_APN_AUTHENTICATION_FAILED	510
MODEM_GPRS_APN_GET_IP_FAILED	511
MODEM_INIT_DATA_CORRUPTED	512
MODEM_FTP_SETUP_CONNECTION_FAILED	513
MODEM_FTP_CONNECT_FAILED	514
MODEM_FTP_TCP_SEND_FAILED	515
MODEM_FTP_GET_FILE_SIZE_FAILED	516
MODEM_FTP_FILE_NOT_FOUND	517
MODEM_FTP_GET_FAILED	518
MODEM_FTP_EXTEND_DOWNLOAD_BUFFER	519
MODEM_FTP_LOGIN_FAILED	520
MODEM_FTP_INVALID_USERNAME_OR_PASSWORD	521
MODEM_FTP_INVALID_DIRECTORY	522
MODEM_FTP_OPEN_DIRECTORY_FAILED	523
MODEM_FTP_PASSIVE_CONNECTION_REQUEST_FAILED	524
MODEM_FTP_PASSIVE_PORT_CONNECTION_FAILED	525
MODEM_FTP_TCP_STORE_COMMAND_PERMISSION_DENIED	526
MODEM_FTP_TCP_STORE_COMMAND_FAILED	527
MODEM_FTP_TCP_RETRIEVE_COMMAND_FAILED	528
MODEM_FTP_TCP_PASSIVE_SEND_FAILED	529
MODEM_FTP_TCP_SENT_FILE_VALIDATION_FAILED	530
MODEM_NTP_UDP_SEND_FAILED	531
MODEM_PIN_IS_DEACTIVATED	532
MODEM_PIN_IS_NOT_DEACTIVATED	533
MODEM_GSM_NETWORK_ERROR	534
MODEM_BAD_SIGNAL	535
MODEM_SMS_CNMI_ERROR	536
MODEM_SMS_CLEAN_STORAGE_ERROR	537
MODEM_SMS_MODE_ERROR	538
MODEM_SMS_CS_ERROR	539

MODEM_SMS_SEND_ERROR	540
MODEM_SMS_RECEIVE_ERROR	541
MODEM_INVALID_IMEI	542
MODEM_GPRS_NOT_STARTED	543
MODEM_GPRS_NOT_TURNED_OFF	544
MODEM_FTP_TYPE_SETTING_ERROR	545
MODEM_PDP_ACTIVATE_ERROR	546
MODEM_DATA_STATE_ERROR	547
MODEM_GPRS_NO_CONNECTION	548
MODEM_TCP_CONNECTION_ERROR	549
MODEM_CLOCK_NOT_ENABLED	550
MODEM_NOT_IN_INITIAL_STATE	551
MODEM_NOT_IN_START_STATE	552
MODEM_NOT_IN_GPRS_STATE	553
MODEM_NOT_IN_STATUS_STATE	554
MODEM_FILE_NOT_FOUND	558
MODEM_UDP_CONNECTION_ERROR	559
MODEM_UDP_CONNECT_FAILED	560
MODEM_TCP_CONNECT_FAILED	561
MODEM_SMS_SET_STORAGE_ERROR	562
MODEM_BLUETOOTH_CMD_ERROR	563
MODEM_BLUETOOTH_STATUS_ERROR	564
MODEM_BLUETOOTH_IS_OFF	565
MODEM_BLUETOOTH_IS_ON	566
MODEM_BLUETOOTH_PAIRING_ERROR	567
MODEM_BLUETOOTH_NO_DEVICE_FOUND	568
MODEM_BLUETOOTH_MESSAGE_OVERFLOW	569
USB_READY	600
USB_NOT_ATTACHED	601
USB_SEND_FAILED	602
READ_ERROR	603
WRITE_ERROR	604
USB_INVALID_MESSAGE	605
EXTERN_FLASH_WRITE_ERROR	10700
EXTERN_FLASH_0xFF_WRITE	701
EXTERN_FLASH_OVERWRITE_FAILED	702
EXTERN_FLASH_CORRUPTED_WRITE	703
EXTERN_FLASH_INVALID_ADDRESS	704
EEPROM_INVALID_ADDRESS	800
EEPROM_WRITE_ERROR	10801
PRINTER_ERR_TEMP	10900
PRINTER_ERR_SENSOR_OPEN	901
PRINTER_ERR_COOLING_DOWN	902
PRINTER_ERR_INVALID_TEXT_FORMAT	903
PRINTER_ERR_INVALID_TEXT_LENGTH	904
PRINTER_ERR_NO_PAPER	905
PRINTER_ADC_MEASUREMENT_FAILED	906

PRINTER_NO_PAPER_PRINTER_TURN_OFF	907
PRINTER_ERR	10907
TSI_THRESHOLD_CALIBRATION_FAILED	11000
TSI_ERR_COLUMN_1	11001
TSI_ERR_COLUMN_2	11002
TSI_ERR_COLUMN_3	11003
TSI_ERR_COLUMN_4	11004
TSI_ERR_COLUMN_5	11005
TSI_ERR_ROW_1	11006
TSI_ERR_ROW_2	11007
TSI_ERR_ROW_3	11008
TSI_ERR_ROW_4	11009
TSI_ERR_ROW_5	11010
I2C_COMMUNICATION_ERROR	11100
RTC_SET_TIME_FAILED	11200
RTC_SET_DATE_FAILED	11201
RTC_SET_ALARM_FAILED	11202
SRAM_INVALID_ADDRESS	1300
PWR_MAIN_SUPPLY_OFF	1400
INIT_RTC_LSI_FAILED	11500
INIT_RTC_LSE_FAILED	11501
INIT_RTC_SYNC_FAILED	11502
INIT_RTC_SET_TIME_FAILED	11503
INIT_RTC_SET_DATE_FAILED	11504
INIT_PRINTER_ADC_FAILED	11505
INIT_UART_FAILED	11506
INIT_DISPLAY_CUSTOMER_FAILED	11507
INIT_DISPLAY_OPERATOR_FAILED	11508
INIT_KEYBOARD_FAILED	11509
INIT_PRINTER_FAILED	11510
INIT_MODEM_FAILED	11511
INIT_RTC_FAILED	11512
INIT_SD_CARD_FAILED	11513
INIT_SRAM_FAILED	11514
INIT_EEPROM_FAILED	11515
TEST_DISPLAY_CUSTOMER_FAILED	11600
TEST_DISPLAY_OPERATOR_FAILED	11601
TEST_KEYBOARD_FAILED	11602
TEST_PRINTER_FAILED	11603
TEST_BARCODE_READER_FAILED	11604
TEST_MODEM_FAILED	11605
TEST_RTC_FAILED	11606
TEST_SD_CARD_FAILED	11607
TEST_FM_FAILED	11608
TEST_SRAM_FAILED	11609
TEST_EEPROM_FAILED	11610
INVALID_COMPORT	1700

COMPORT_TIMEOUT	1701
COMPORT_BUFFER_OVERFLOW	1702
COMPORT_WRITE_ERROR	1703
COMPORT_CLOSE_ERROR	1704
INVALID_COMMAND	1705
NO_ITEM	1706
START_DATE_WRONG_FORMAT	1707
START_DATE_MISSING	1708
END_DATE_WRONG_FORMAT	1709
END_DATE_MISSING	1710
NON_FISCAL_DOCUMENT_MISSING	1711
NO_RECEIPT_ITEMS	1712
NO_RECEIPT_ITEM	1713
INVALID_RECEIPT_ITEM_QUANTITY	1714
INVALID_RECEIPT_ITEM_DISCOUNT	1715
INVALID_ITEM_NAME	1716
INVALID_ITEM_PRICE	1717
INVALID_ITEM_TAX	1718
NO_PAYMENT	1719
INVALID_PAYMENT_TYPE	1720
INVALID_AMOUNT	1721
INVALID_CUSTOMER_DATA	1722
NO_FISCAL_SERVICE	1723
INVALID_CANCELED_ITEM	1724
INVALID_ITEM_PLU	1725
INVALID_ITEM_BARCODE	1726
SLEEP_OCCURED_ERROR	1800
INTERNAL_FLASH_WRITE_ERROR	1900
INTERNAL_FLASH_CLEAR_PAGE_ERROR	1901
CRYPT_ERROR	2000
CRYPT_BASE64_ERROR	2001
EBON_TRANSCATION_INTERRUPTED	3099
EBON_ERROR	3100
EBON_FAILED	3101
EBON_INTERNET_IS_DOWNND	3102
EBON_PAGE_NOT_FOUND	3110
EBON_REQUEST_ID_NOT_EXIST	3120
EBON_REQUEST_ID_NOT_VALID	3121
EBON_REQUEST_ID_EXPIRED	3122
EBON_USERNAME_OR_PASSWORD_NULL_OR_EMPTY	3150
EBON_USERNAME_NOT_EXIST	3151
EBON_PASSWORD_NOT_VALID	3152
EBON_IPADDRESS_NOT_VALID	3153
EBON_USER_AND_APP_MISSMATCH	3154
EBON_USER_BLOCKED	3160
EBON_USER_ACCESS_DENIED	3161
EBON_USER_NOT_EXIST	3162

EBON_COMMON_USER_NOT_DELETE	3163
EBON_NUMBER_NULL_OR_EMPTY	3200
EBON_NUMBER_NOT_VALID	3201
EBON_NUMBER_ALLREADY_EXIST	3202
EBON_PIN_NULL_OR_EMPTY	3210
EBON_PIN_NOT_VALID	3211
EBON_AMOUNT_NULL_OR_EMPTY	3220
EBON_AMOUNT_NOT_VALID	3221
EBON_AMOUNT_NOT_ENOUGH	3222
EBON_EXCEEDED	3223
EBON_CURRENT_CREDIT_LIMIT	3224
EBON_PARTNER_CURRENT_CREDIT_LIMIT	3225
EBON_WEB_SERVICE_EXCEPTION_ERROR	3230
EBON_PROVIDER_REMOTE_SERVICE_PROBLEM	3231
EBON_PROVIDER_SERVICE_EXCEPTION_ERROR	3232
EBON_PROVIDER_USER_NOT_REGISTERED	3234
EBON_PROVIDER_WRONG_PROVIDER	3235
EBON_PROVIDER_INCORRECT_NUMBER	3236
EBON_PROVIDER_INVALID_PARAMETER	3237
EBON_CREATE_NEW_TRANSACTION_ERROR	3238
EBON_STORNO_PROBLEM	3240
EBON_STORNO_TIME_EXPIRED	3241
EBON_TRANSACTION_ALREADY_STORNOED	3242
EBON_TRANSACTION_NOT_FOUND	3250
EBON_TRANSACTION_LIST_EMPTY	3251
EBON_TRANSACTION_ID_NULL_OR_EMPTY	3252
EBON_PROVIDER_TRANSACTION_ID_NULL_OR_EMPTY	3253
EBON_TRANSACTION_IN_PROGRESS	3254
EBON_DATES_NULL_OR_EMPTY	3260
EBON_ALL_INPUTS_NULL_OR_EMPTY	3261
EBON_WEB_SERVICE_ADD_ALARM_ERROR	3300

**Opis problema/rješenja**

Fajl na SD kartici nije završen. Potrebno na SD kartici pronaći fajl s kapacitetom "0" te isti i obrisati, često je dovoljno da se SD kartica zbaci u PC

SD kartica nije inicializovana, potrebno ubaciti u PC te vratiti u FU

Uređaj ne vidi SD karticu, provjeriti da li je kartica na svom mjesti (da nije iskočila), moguće da se ne može očitati ni na PC-u, pokušati popravak sd kartice ili spasiti podatke, formatirati SD karticu te podatke ponovo vratiti na karticu.

Zabranjen upis na SD karticu, spasiti podatke pokušati formatirati ili prebaciti podatke na drugu SD karticu ako je moguće

Oštećena FAT tabela, pokušati popravak pomoću alata sa linka:

[http://www.kase.ba/Download/power\\_toll.zip](http://www.kase.ba/Download/power_toll.zip)

Nedostaje fajl na SD kartici. Ukoliko je zamjena FM onda je obavezno upisati IMEI. Također može da nedostaje Zaglavlje (podaci o firmi) ukoliko javlja odmah nakon uključanja, a ukoliko javi grešku prilikom početka prenosa onda nedostaje komanda terminala ili postavke terminala

Ovaj problem može biti uzrokovan punjenjem memorije, prekidom štampe u slučaju nestanka papira i slično. Kada utvrdimo da je sve navedeno ispravno tada se može reći da je neispravan EEPROM ali prije toga je potrebno pokušati ubaciti NEFISKALIZOVANU FM (iz novog uređaja), resetovati na tipku, te resetovati kroz aplikaciju sa "Novom FM" i upisati vrijeme te vratiti originalnu FM, resetovati na tipku i ponovo upisati vrijeme.



Neispravni brojači. Pokušati reset kroz aplikaciju ako ne uspijeva onda ubaciti "**NEFISKALIZOVANU FM**" (ne može FM lager, ali odgovara od novog uređaja Tone,T202, FP1Plus za sva tri uređaja odgovara ista)

Telethings prijenos nije moguć jer nema komunikacije između FU i TFS. Nekompatibilna verzija FW i TFS.

Neispravna komanda koja je preuzeta sa FTP servera

Nema odgovora s FTP servera ili GSM mreže

GPRS modul se ne može uključiti (fizički problem s GPRS terminalom ili Konektorom terminala)

PIN kod nije deaktiviran na SIM kartici

Nema SIM kartice ili je terminal ne vidi (provjeriti holder SIM kartice i drugu sim karticu ako je OK ide zamjena terminal)

Nema GPRS mreže (kartica može biti aktivna ali neispravna), postavke neispravne

Nema konekcije s FTP serverom, uzrok može biti signal, problemi na mreži ili sim kartica

Registрован na mrežu i prijavljen na FTP ali ne može da uspostavi konekciju (problem s mrežom)

Nemoguća prijava na FTP server (mreža može biti problem ili postavke terminala)

Postoji fajl na FTP serveru s istim nazivom (TFS nedozvoljava upis fajla)

Ne može se prebaciti u pasivni mod za prijenos (problem s mrežom)

Slab signal ili neispravna SIM kartica (možda aktivna ali neispravna)

Potrebno unijeti kod IMEI generisan na portalu  
Slab signal ili neispravna SIM kartica (možda aktivna ali neispravna)

Provjeriti postavke terminala (pristupni podaci mneispravni)

Nema papira ili printer nije uključen na napajanje ili na prekidač  
Printer neispravan, fizički oštećen printer ili flat kabel

Eeprom neispravan ili nema komunikaciju s displejom

Vrijeme na printeru ne radi (kvarc ili veza do procesora neispravna)

Nije odabran comport (vrijedi za linux i android)





## LISTA GREŠAKA KOJE VRAĆA TFS

Nema_operatera	0
Logiran_operater	1
Printanje_dnevnog_izvjestaja	10
Printanje_presjeka_stanja	11
Printanje_periodicnog_izvjestaja	12
Printanje_duplikata_dnevnog_izvjestaja	13
Printanje_duplikata_presjeka_stanja	14
Printanje_duplikata_periodicnog_izvjesca	15
Printanje_fiskalnog_racuna	16
Printanje_duplikata_fiskalnog_racuna	17
Printanje_reklamiranog_racuna	18
Printanje_duplikata_reklamiranog_racuna	19
Printanje_izvjestaja_po_operaterima	22
Printanje_zaglavljja_nefiskalnog_teksta	30
Printanje_nefiskalnog_teksta	31
Printanje_podnozja_nefiskalnog_teksta	32
Printanje_testnog_dokumenta	33
Printanje_izvjestaja_po_artiklima	20
Printanje_duplikata	99
Spremanje_na_SD	101
Prodaja	102
Prodaja_bez_kusura	103
Prodaja_sa_kusurom	104
Kraj_racuna	105
Fiskalna_memorija_puna_Dnevni_izvjestaji	110
Fiskalna_memorija_puna_Servisi	111

Fiskalna_memorija_puna_Reseti	112
Fiskalna_memorija_puna_PoreskeStope	113
Elektronski_zurnal_pun	114
Elektronski_zurnal_pun_DI	115
Elektronski_zurnal_pun_DI_PI	116
Elektronski_zurnal_pun_DI_PI_Potvrda	117
Nekomatibilna verzija TFS i Firmwera	137
SD_backup	118

Odgovor_na_Get_info	40
Komunikacija_sa_modemom	50
Slanje_SALE_datoteke	51
Slanje_INOVICE_datoteke	52
Slanje_RESET_datoteke	53
Slanje_TAX_datoteke	54
Slanje_SERV_datoteke	55

Preuzimanje_CMD_datoteke	56
Printanje_potvrde_uspjesnog_prenosa	70
Kriticna_greska	255

Nepoznata_greska	499
Veza_sa_printerom_u_prekidu	400
Operator_nije_logiran	401
Neispravno_vrijeme	410
Vrijeme_manje_od_vremena_fiskalizacije	411
Napravite_dnevni_izvjestaj	412
Greska_fiskalne_memorije	413
Uredjaj_je_vec_fiskaliziran	414
Porezna_grupa_ne_postoji	415
Nema_elektronskog_zurnala_Pogresan_parametar	416
Nema_servisnog_jumpera	417
Pogresno_vrijeme	418
Uredjaj_nije_fiskaliziran	419
Problem_sa_elektronskim_zurnalom	420
Vrijeme_manje_od_vremena_fiskalizacije_2	430
DST_vec_promijenjeno	431
Fiskalna_memorija_puna_porezi	440
Fiskalna_memorija_puna_izvjestaji	441
Fiskalna_memorija_puna_reseti	442
Fiskalna_memorija_puna_servisi	443
Porezne_stope_iste	470



Operator_nije_logiran_2	655
Greska_Fiskalna_Memorija_Elektronski_Zurnal_Modem	500
Neispravno_vrijeme_2	501
Neispravno_Fiskalno_Vrijeme	502
Nema_papira	503
Visoka_Temperatura_Printera	504
Maximalan_Broj_Dnevni Izvjestaja	505
Maximalan_Broj_Reseta	506
Nepoznata_Greska	507
Neispravna_Komanda	508
Nedefinirana_Porezna_Grupa	509
Nedefiniran_Artikal	510
Maximalan_broj_artikala_dostignut	511
Kolicina_cijena_0_Displej_u_kvaru_Placanje_0	512
Prekoracenje_cijene_kolicine_placanja	513
Prekoracenje_u_dnevnom_totalu	514
Prekoracenje_u_prodaji_ili_placanju	515
Prekoracenje_stavki_racuna_ili_reklamacije	516
Prekoracenje_u_iznosu_reklamacije	517
Ne_postoji_artikal_za_reklamaciju_Problem_rabata_Greska_u_nefiskalnom_izvjestaju	518
Napravite_dnevni_izvjestaj_Skinite_servisni_jumper_IOSA_nije_uredu	519
Format_kolicine_nije_uredu_Maximalan_Broj_klijenata_u_RAM	520
Prekoracenje_iznosa_placanja	521
Pogresna_vrsta_placanja_Servis_u_toku_Nedozvoljeni_rezim	522
Placanja_karticom_ili_cekom_vece_od_iznosa_racuna	523
Ukupna_suma_placanja_veca_od_sume_racuna	524
Pogresna_komanda_za_trenutni_status	525
Pogresan_parametar	526
Problem_sa_terminalom_nema_odgovora	527
Elektronski_zurnal_nema_konekcije	528
Elektronski_zurnal_je_pun	529
Problem_sa_prodajom_ili_dodavanjem_novog_artikla	530
Elektronski_zurnal_prazan_ili_je_zamjenjen	531
Problem_sa_satom_realnog_vremena	532
Problem_SRAM	533
Problem_pri_inicijalizaciji	534
Nedovoljno_novca_u_kasi	535
Iznos_poreske_stope_u_nedozvoljenim_granicama	536
Vrijeme_manje_od_vremena_zadnjeg_fiskalnog_dokumenta	537
Problem_sa_terminalom_Neispravan_pin	538
Problem_sa_terminalom_Neispravna_SIM_kartica	539

Problem_sa_terminalom_GPRS_mreza_nedostupna	540
Nelegalna_verzija_programske_memorije	541
Problem_sa_slanjem_datoteke	542
Brojaci_fiskalne_memorije_nisu_uredu	543
Trenutne_vrijednosti_poreznih_stopa_nisu_uredu	544
Brojaci_transfera_nisu_uredu	545
Problem_sa_LCD_displayem	546
Uredaj_u_servisnom_modu	547
Backup_problem	548
FTP_Problem_sa_logiranjem	549
FTP_Problem_sa_direktorijem	550
FTP_Problem_sa_citanjem_datoteke	551
FTP_Problem_sa_upisom_datoteke	552
Nema_podataka_za_stampu	553
Elektronski_zurnal_nema_dovoljno_memorije	554
Elektronski_zurnal_pun_stampati_DI	555
Terminal_zamijenjen	556
Problem_pri_upisu_osnovnih_postavki_terminala	557
Problem_pri_upisu_IMEI	558
Neispravne_postavke_terminala	559
Problem_neispravan_MD5	560
Problem_pri_kreiranju_invoice	561
FTP_Problem_datoteka_vec_postoji	562
FTP_Problem_sa_konekcijom	563
FTP_Problem_CIPSTATUS_not_CONNECTED	564
FTP_Problem_550_Permission_denied	565
FTP_problem_FTPusername	566
FTP_problem_FTPpassword	567
FTP_problem_PassiveConnection	568
Problem_pri_upisu_osnovnih_postavki_terminala_baudrate	569
Problem_pri_upisu_osnovnih_postavki_terminala_sfc	570
Problem_pri_upisu_osnovnih_postavki_terminala_echo	571
Problem_pri_upisu_osnovnih_postavki_terminala_store	572
Jedna_vrsta_placanja_sa_iznosom_0_potrebna_za_reklamaciju	573
Promet_nije_uredu	574
Nema_odgovora	575
Secure_nije_spremljen	576
FD_nije_spremljen	577

TT_nepoznata_Greška	4000
TT_Server_nedostupan	4001
TT_Nema_odgovora	4002
TT_Pristup_zabranjen	4003









Potrebno provjeriti zaglavlje i ctrl+shift+s (SECURE OK)  
Provjeriti kapacitet i slobodan prostor na elektronskom žurnalu

Potrebno provjeriti zaglavlje





Problem na TT serveru, nije u finkciji ili nije dostupan

Problem na TT serveru, nije u finkciji ili nije dostupan

Potrebno dodati uređaj na TT (IBFM nije na listi uređaja)