

```

#!/bin/bash
#
# run_all_tests.sh - automates building every glossary section's own unit
# test group through MAME, one at a time, capturing each group's output
# to its own log file.
#
# Requires: lwasm, python3. Assumes forth6809.asm
# All overridable, run with --help to see every flag.
#

set -uo pipefail

# -----
# Configuration - built-in defaults, all overridable from the command
# line below (run with --help to see every flag)
# -----
ASM_SOURCE="forth6809.asm"
LWASM_BIN="lwasm"
SERIALPOLL=1
SCRIPT_DIR="$(cd "$(dirname "${BASH_SOURCE[0]}")" && pwd)"

usage() {
    cat <<EOF2
Usage: $0 [OPTIONS]

All options have built-in defaults (shown below); only pass what you
need to override for your own machine.

    --asm-source PATH          Path to forth6809.asm (default: $ASM_SOURCE)
    --lwasm-bin PATH          lwasm executable (default: $LWASM_BIN)
    --serialpoll 0|1          Serial driver to build: 1 = polled, 0 = interrupt
                              driven (default: $SERIALPOLL)
    -h, --help                Show this help and exit
EOF2
}

while [[ $# -gt 0 ]]; do
    case "$1" in
        --asm-source)    ASM_SOURCE="$2"; shift 2 ;;
        --lwasm-bin)     LWASM_BIN="$2"; shift 2 ;;
        --serialpoll)    SERIALPOLL="$2"; shift 2 ;;
        -h|--help)       usage; exit 0 ;;
        *)               echo "Unknown option: $1" >&2; usage; exit 1 ;;
    esac
done

```

```

done

if [[ "$SERIALPOLL" != "0" && "$SERIALPOLL" != "1" ]]; then
    echo "--serialpoll must be 0 or 1 (got '$SERIALPOLL')>" >&2
    exit 1
fi

# Glossary section names, in TSTSELECTOR order (0-17), matching the
# table in the ClaudeForth documentation's own Build Instructions
# section - used only for readable log file names and the summary.
SECTION_NAMES=(
    "3.1_SysIO" "3.2_Stack" "3.3_RetStack" "3.4_SArith" "3.5_DArith"
    "3.6_Logic" "3.7_Compare" "3.8_CtrlFlow" "3.9_DefWords" "3.10_CompWords"
    "3.11_Memory" "3.12_StrParse" "3.13_NumOut" "3.14_BaseRadix"
    "3.15_Exception" "3.16_Comments" "3.17_EnvSys" "3.18_Tools"
)

echo "SERIALPOLL=$SERIALPOLL"

# -----
# Main loop
# -----

declare -a RESULTS

for ((n=0; n<18; n++)); do

    name="${SECTION_NAMES[$n]}"

    echo "=====
    echo "=== TSTSELECTOR=$n ($name) ==="
    echo "=====

    # Step 1: assemble this specific test group into the ROM image
    "$LWASM_BIN" --6809 --format=raw --output=forth6809."$n".bin \
        --list=forth6809.lst \
        --define=SERIALPOLL="$SERIALPOLL" \
        --define=UNITTESTS=1 --define=TSTSELECTOR="$n" \
        "$ASM_SOURCE"
    if [ $? -ne 0 ]; then
        echo "FAIL: lwasm failed for TSTSELECTOR=$n"
        RESULTS+=("$n $name ASSEMBLE_FAIL")
        continue
    fi

    echo

done

```

